

A SECOND-ORDER STOCHASTIC MAXIMUM PRINCIPLE FOR GENERALIZED MEAN-FIELD SINGULAR CONTROL PROBLEM

HANCHENG GUO*

Department of Mathematics, Faculty of Science and Technology
University of Macau
Macau, 999078, P. R. China

JIE XIONG

Department of Mathematics, Faculty of Science and Technology
University of Macau
Macau, 999078, P. R. China

(Communicated by the associate editor name)

ABSTRACT. In this paper, we study the generalized mean-field stochastic control problem when the usual stochastic maximum principle (SMP) is not applicable due to the singularity of the Hamiltonian function. In this case, we derive a second order SMP. We introduce the adjoint process by the generalized mean-field backward stochastic differential equation. The keys in the proofs are the expansion of the cost functional in terms of a perturbation parameter, and the use of the range theorem for vector-valued measures.

1. Introduction. We consider the following optimal stochastic control problem of mean-field type with the state equation

$$\begin{cases} dX_t = b(t, X_t, P_{X_t}, v_t)dt + \sigma(t, X_t, P_{X_t})dB_t, \\ X_0 = x, \end{cases} \quad (1)$$

and the cost functional

$$J(v) = \mathbb{E} \left\{ \int_0^T h(t, X_t, P_{X_t}, v_t)dt + \Phi(X_T, P_{X_T}) \right\}, \quad (2)$$

where P_ξ denotes the law of the random variable ξ .

The agent wishes to minimize his cost functional, namely, an admissible control $u \in \mathcal{U}$ is said to be optimal if

$$J(u) = \min_{v \in \mathcal{U}} J(v).$$

where $\mathcal{U}$ is the set of all admissible controls to be defined later in Section 3.

About stochastic maximum principle (SMP), some pioneering works have been done by Pontryagin et al. [22]. They obtained Pontryagin's maximum principle by using "spike variation". Kushner ([14], [15]) studied the SMP in the framework

2010 *Mathematics Subject Classification.* Primary: 93E20, 93E03, 60H30; Secondary: 70G70.

Key words and phrases. Stochastic maximum principle, mean-field control problem, singular control, Fréchet derivative, range theorem of vector-valued measures.

Research supported partially by FDCT 025/2016/A1.

* Corresponding author: Hancheng Guo.

when the diffusion coefficient does not depend on the control variable, and the cost functional consists of terminal cost only. Haussmann [10] gave a version of SMP when the diffusion of the state does not depend on the control variable. Arkin and Saksonov [1], Bensoussan [3] and Bismut [4], proved different versions of SMP under various setups. An SMP was obtained by Peng [21] in 1990. In that paper, first and second order variational inequalities are introduced, when the control domain need not to be convex, and the diffusion coefficient contains the control variable.

Pardoux and Peng [20] introduced non-linear backward stochastic differential equations (BSDE) in 1990. They showed that under appropriate assumptions, BSDE admits an unique adapted solution, and the associated comparison theorem holds. Buckdahn et al [6] obtained mean-field BSDE in a natural way as the limit of some high dimensional system of forward and backward stochastic differential equations. Li [16] studied SMP for mean-field controls when the domain of the control is assumed to be convex. Under some additional assumptions, both necessary and sufficient conditions for the optimality of a control were proved. Buckdahn et al [7] studied generalized mean-field stochastic differential equations and the associated partial differential equations (PDEs). “Generalized” means that the coefficients depend on both the state process and its law. They proved that under appropriate regularity conditions on the coefficients, the SDE has a unique classical solution. Buckdahn et al. [5] obtained SMP for generalized mean-field system in 2016.

Sometimes, the Hamiltonian function becomes constant in the control variable, as we will see in the next example, which makes the aforementioned SMP not applicable.

Example 1.1. Consider the control problem with state equation:

$$\begin{cases} dX_t^v &= v_t dt + \{(X_t^v - 1) + \mathbb{E}[(X_t^v - 1)]\} dB_t, \quad v \in U := \{-1, 0, 1\}, \\ X_0^v &= 1, \end{cases} \quad (3)$$

and cost functional:

$$J(v) = \frac{1}{2} \mathbb{E} \{ (X_T^v - 1) + \tilde{\mathbb{E}}[(X_T^v - 1)] \}^2.$$

For the control $u_t \equiv 0$, $X_t^u \equiv 1$ is the unique solution of (3). It is clear that $J(u) = 0$, and hence, u is an optimal control. On the other hand, the first order adjoint processes satisfy the following equation:

$$\begin{cases} dp_t &= \{q_t + \mathbb{E}[q_t]\} dt - q_t dB_t \\ p_T &= 0. \end{cases} \quad (4)$$

Clearly $(p_t, q_t) \equiv (0, 0)$ is the solution. Therefore

$$H(t, X_t^u, P_{X_t^u}, p_t, q_t, v) \equiv 0, \quad v \in U.$$

which makes the SMP useless in charactering the optimal control $u_t = 0$. $\square$

Now, we discuss singular optimal stochastic controls defined as follows.

Definition 1.2. An admissible control $\tilde{u}(\cdot)$ is singular on region V if $V \subset U$ is of positive measure and for a.e. $t \in [0, T]$ and $v \in V$, we have for any $v \in V$,

$$H(t, X_t^{\tilde{u}}, P_{X_t^{\tilde{u}}}, p_t^{\tilde{u}}, q_t^{\tilde{u}}, \tilde{u}_t) = H(t, X_t^{\tilde{u}}, P_{X_t^{\tilde{u}}}, p_t^{\tilde{u}}, q_t^{\tilde{u}}, v), \quad a.s. \quad (5)$$

As we have seen in last example, the SMP is not very useful under singular control. Our goal is to derive further necessary condition for optimality. We shall call the original SMP as the first order SMP while the one we will derive as the second order one.

For second-order SMP of singular control problems, Bell [2], Gabasov [9], Kazemi-Dehkordi [12], Krener [13], Mizukami and Wu [19] devoted themselves to the deterministic case. Lu [17] interested in second order necessary conditions for stochastic evolution system. Tang [23] studied the singular optimal control problem for stochastic system with state equation

$$\begin{cases} dX_t = b(t, X_t, v_t)dt + \sigma(t, X_t)dB_t, \\ X_0 = x. \end{cases} \quad (6)$$

and the cost functional

$$J(v) = \mathbb{E}\left\{\int_0^T h(t, X_t, v_t)dt + \Phi(X_T)\right\}, \quad (7)$$

By applying spike variation and vector-value measure theory, a second-order maximum principle is presented which involves the second-order adjoint process.

In this paper, we study the case when the state equation and the cost functional are in generalized mean-field form. The rest of this paper is organized as follows: In Section 2, we introduce the preliminaries about the generalized mean-field BSDEs. In Section 3, we set up the formulation of the singular optimal stochastic control problem and state the main result of the paper. Section 4 is devoted to the study of the impact of the control actions on the state and the cost functional by using Taylor's expansion. In that section, we also present some estimations about the state. In Section 5, the method in Section 4 is reused for the expansion of the cost functional with respect to the control variable. Sections 6 is devoted to the proof of the second order stochastic maximum principle.

2. Preliminaries. In this section, for the convenience of the reader, we state some results of Buckdahn et al. [7] without proofs.

Let $\mathcal{P}_2(\mathbb{R}^n)$ be the collection of all square integrable probability measures over $(\mathbb{R}^n, \mathcal{B}(\mathbb{R}^n))$, endowed with the 2-Wasserstein metric W_2 , which is defined as

$$W_2(P_\mu, P_\nu) = \inf \left\{ \left(\mathbb{E}[|\mu' - \nu'|^2] \right)^{\frac{1}{2}} \right\},$$

for all $\mu', \nu' \in L^2(\mathcal{F}_0; \mathbb{R}^d)$ with $P_{\mu'} = P_\mu$, $P_{\nu'} = P_\nu$. Denote by $L^2(\mathcal{F}; \mathbb{R}^n)$ the collection of all $\mathbb{R}^n$ -valued square integrable random variables. The following definition is taken from Cardaliaguet [8].

Definition 2.1. A function $f : \mathcal{P}_2(\mathbb{R}^n) \rightarrow \mathbb{R}$ is said to be differentiable in $\mu \in \mathcal{P}_2(\mathbb{R}^n)$ if, the function $\tilde{f} : L^2(\mathcal{F}; \mathbb{R}^n) \rightarrow \mathbb{R}$ given by $\tilde{f}(\mathbf{v}) = f(P_{\mathbf{v}})$ is differentiable (in Fréchet sense) at $\mathbf{v}_0$, defined by $P_{\mathbf{v}_0} = \mu$, i.e. there exists a linear continuous mapping $D\tilde{f}(\mathbf{v}_0) : L^2(\mathcal{F}; \mathbb{R}^n) \rightarrow \mathbb{R}$, such that

$$\tilde{f}(\mathbf{v}_0 + \eta) - \tilde{f}(\mathbf{v}_0) = D\tilde{f}(\mathbf{v}_0)(\eta) + o(|\eta|_{L^2}),$$

with $|\eta|_{L^2} \rightarrow 0$ for $\eta \in L^2(\mathcal{F}; \mathbb{R}^n)$.

According to the Riesz representation theorem, there exists a unique random variable $\theta_0 \in L^2(\mathcal{F}; \mathbb{R}^n)$ such that $D\tilde{f}(\mathbf{v}_0)(\eta) = (\theta_0, \eta)_{L^2} = \mathbb{E}[\theta_0 \eta]$, for all $\eta \in L^2(\mathcal{F}; \mathbb{R}^n)$. In [8] it has been proved that there is a Borel function $h_0 : \mathbb{R}^n \rightarrow \mathbb{R}^n$ such that $\theta_0 = h_0(\mathbf{v}_0)$ a.s. Then,

$$f(P_{\mathbf{v}}) - f(P_{\mathbf{v}_0}) = \mathbb{E}[h_0(\mathbf{v}_0)(\mathbf{v} - \mathbf{v}_0)] + o(|\mathbf{v} - \mathbf{v}_0|_{L^2}), \quad \mathbf{v} \in L^2(\mathcal{F}; \mathbb{R}^n).$$

We call $\partial_\mu f(P_{\mathbf{v}_0}, y) := h_0(y)$, $y \in \mathbb{R}^n$, the derivative of $f : \mathcal{P}_2(\mathbb{R}^n) \rightarrow \mathbb{R}$ at $P_{\mathbf{v}_0}$. Note that $\partial_\mu f(P_{\mathbf{v}_0}, y)$ is $P_{\mathbf{v}_0}(dy)$ -a.s. uniquely determined.

For mean-field type SDE and BSDE, we introduce the following notations. Let $(\Omega', \mathcal{F}', P')$ be a copy of the probability space $(\Omega, \mathcal{F}, P)$. For each random variable ξ over $(\Omega, \mathcal{F}, P)$ we denote by ξ' a copy of ξ defined over $(\Omega', \mathcal{F}', P')$. $\mathbb{E}'[\cdot] = \int_{\Omega'} (\cdot) dP'$ acts only over the variables ω' .

Definition 2.2. We say that $f \in C_b^{1,1}(\mathcal{P}_2(\mathbb{R}^d))$ (continuously differentiable over $\mathcal{P}_2(\mathbb{R}^d)$ with Lipschitz-continuous bounded derivative), if for all $\mathbf{v} \in L^2(\mathcal{F}, \mathbb{R}^d)$, there exists a $P_{\mathbf{v}}$ -modification of $\partial_{\mu}f(P_{\mathbf{v}}, \cdot)$, again denote by $\partial_{\mu}f(P_{\mathbf{v}}, \cdot)$, such that $\partial_{\mu}f : \mathcal{P}_2(\mathbb{R}^d) \times \mathbb{R}^d \rightarrow \mathbb{R}^d$ is bounded and Lipschitz continuous, i.e., there is a real constant C such that

$$\begin{aligned} i) \quad & |\partial_{\mu}f(\mu, x)| \leq C, \quad \forall \mu \in \mathcal{P}_2(\mathbb{R}^d), x \in \mathbb{R}^d, \\ ii) \quad & |\partial_{\mu}f(\mu, x) - \partial_{\mu}f(\mu', x')| \leq C(W_2(\mu, \mu') + |x - x'|), \\ & \forall \mu, \mu' \in \mathcal{P}_2(\mathbb{R}^d), x, x' \in \mathbb{R}^d; \end{aligned} \quad (8)$$

we call this function $\partial_{\mu}f$ the derivative of f .

Given $f \in C_b^{1,1}(\mathcal{P}_2(\mathbb{R}^d))$, and $y \in \mathbb{R}^d$, the question of the differentiability of its components $(\partial_{\mu}f)_j(\cdot, y) : \mathcal{P}_2(\mathbb{R}^d) \rightarrow \mathbb{R}$, $1 \leq j \leq d$, raises. This can be discussed in the same way as the first order derivative $\partial_{\mu}f$ above. If $(\partial_{\mu}f)_j(\cdot, y) : \mathcal{P}_2(\mathbb{R}^d) \rightarrow \mathbb{R}$ belongs to $C_b^{1,1}(\mathcal{P}_2(\mathbb{R}^d))$, we have that its derivative $\partial_{\mu}((\partial_{\mu}f)_j(\cdot, y))(\cdot, \cdot) : \mathcal{P}_2(\mathbb{R}^d) \times \mathbb{R}^d \rightarrow \mathbb{R}^d$ is a Lipschitz-continuous function. Then

$$\partial_{\mu}^2 f(\mu, x, y) := (\partial_{\mu}((\partial_{\mu}f)_j(\cdot, y))(\mu, x))_{1 \leq j \leq d}, \quad (\mu, x, y) \in \mathcal{P}_2(\mathbb{R}^d) \times \mathbb{R}^d \times \mathbb{R}^d,$$

defines a function $\partial_{\mu}^2 f : \mathcal{P}_2(\mathbb{R}^d) \times \mathbb{R}^d \times \mathbb{R}^d \rightarrow \mathbb{R}^d \otimes \mathbb{R}^d$.

Definition 2.3. We say that $f \in C_b^{2,1}(\mathcal{P}_2(\mathbb{R}^d))$, if $f \in C_b^{1,1}(\mathcal{P}_2(\mathbb{R}^d))$ and

- i) $(\partial_{\mu}f)_j(\cdot, y) \in C_b^{1,1}(\mathcal{P}_2(\mathbb{R}^d))$, for all $y \in \mathbb{R}^d$, $1 \leq j \leq d$, and $\partial_{\mu}^2 f : \mathcal{P}_2(\mathbb{R}^d) \times \mathbb{R}^d \times \mathbb{R}^d \rightarrow \mathbb{R}^d \otimes \mathbb{R}^d$ is bounded and Lipschitz-continuous;
- ii) $(\partial_{\mu}f)(\mu, \cdot) : \mathbb{R}^d \rightarrow \mathbb{R}^d$ is differentiable for every $\mu \in \mathcal{P}_2(\mathbb{R}^d)$, and its derivative $\partial_y \partial_{\mu}f : \mathcal{P}_2(\mathbb{R}^d) \times \mathbb{R}^d \rightarrow \mathbb{R}^d \otimes \mathbb{R}^d$ is bounded and Lipschitz-continuous.

Example 2.4. For twice continuously differentiable functions $h : \mathbb{R}^d \rightarrow \mathbb{R}$ and $g : \mathbb{R} \rightarrow \mathbb{R}$ with bounded derivatives. Consider $f(P_{\mathbf{v}}) := g(\mathbb{E}[h(\mathbf{v})])$, $\mathbf{v} \in L^2(\mathcal{F}; \mathbb{R}^d)$. Then, given any $\mathbf{v}_0 \in L^2(\mathcal{F}; \mathbb{R}^d)$, $\tilde{f}(\mathbf{v}) := f(P_{\mathbf{v}}) = g(\mathbb{E}[h(\mathbf{v})])$ is Fréchet differentiable in $\mathbf{v}_0$, and

$$\begin{aligned} \tilde{f}(\mathbf{v}_0 + \eta) - \tilde{f}(\mathbf{v}_0) &= \int_0^1 g'(\mathbb{E}[h(\mathbf{v}_0 + s\eta)]) \mathbb{E}[h'(\mathbf{v}_0 + s\eta)\eta] ds \\ &= g'(\mathbb{E}[h(\mathbf{v}_0)]) \mathbb{E}[h'(\mathbf{v}_0)\eta] + o(|\eta|_{L^2}) \\ &= \mathbb{E}[g'(\mathbb{E}[h(\mathbf{v}_0)]) h'(\mathbf{v}_0)\eta] + o(|\eta|_{L^2}). \end{aligned}$$

So, $D\tilde{f}(\mathbf{v}_0)(\eta) = \mathbb{E}[g'(\mathbb{E}[h(\mathbf{v}_0)]) h'(\mathbf{v}_0)\eta]$, $\eta \in L^2(\mathcal{F}; \mathbb{R}^d)$, i.e.,

$$\partial_{\mu}f(P_{\mathbf{v}_0}, y) = g'(\mathbb{E}[h(\mathbf{v}_0)]) (\partial_y h)(y), y \in \mathbb{R}^d.$$

Similarly, we see that

$$\partial_{\mu}^2 f(P_{\mathbf{v}_0}, x, y) = g''(\mathbb{E}[h(\mathbf{v}_0)]) (\partial_x h)(x) \times (\partial_y h)(y),$$

and

$$\partial_y \partial_{\mu}f(P_{\mathbf{v}_0}, y) = g'(\mathbb{E}[h(\mathbf{v}_0)]) (\partial_y^2 h)(y).$$

Let us now consider a complete probability space $(\Omega, \mathcal{F}, P)$ on which we define a d -dimensional Brownian motion $B = (B^1, \dots, B^d) = (B_t)_{t \in [0, T]}$, where $T \geq 0$ denotes an arbitrarily fixed time horizon. We make the following assumptions: There is a sub- σ -field $\mathcal{F}_0 \subset \mathcal{F}$ such that

- i) the Brownian motion B is independent of $\mathcal{F}_0$, and
- ii) $\mathcal{F}_0$ is “rich enough”, i.e., $\mathcal{P}_2(\mathbb{R}^d) = \{P_{\mathbf{v}}, \mathbf{v} \in L^2(\mathcal{F}_0; \mathbb{R}^d)\}$.

By $\mathbb{F} = (\mathcal{F}_t)_{t \in [0, T]}$ we denote the filtration generated by B , completed and augmented by $\mathcal{F}_0$.

Given deterministic Lipschitz functions $\sigma : \mathbb{R}^d \times \mathcal{P}_2(\mathbb{R}^d) \rightarrow \mathbb{R}^{d \times d}$ and $b : \mathbb{R}^d \times \mathcal{P}_2(\mathbb{R}^d) \rightarrow \mathbb{R}^d$, we consider for the initial state $(t, x) \in [0, T] \times \mathbb{R}^d$ and $\xi \in L^2(\mathcal{F}_t; \mathbb{R}^d)$ the stochastic differential equations (SDEs)

$$X_s^{t, \xi} = \xi + \int_t^s \sigma(X_r^{t, \xi}, P_{X_r^{t, \xi}}) dB_r + \int_t^s \sigma(X_r^{t, \xi}, P_{X_r^{t, \xi}}) dr, \quad s \in [t, T], \quad (9)$$

and

$$X_s^{t, x, \xi} = x + \int_t^s \sigma(X_r^{t, x, \xi}, P_{X_r^{t, \xi}}) dB_r + \int_t^s \sigma(X_r^{t, x, \xi}, P_{X_r^{t, \xi}}) dr, \quad s \in [t, T]. \quad (10)$$

It is well-known that under the assumptions above both SDEs have unique solutions in $\mathcal{S}^2([t, T]; \mathbb{R}^d)$, which is the space of $\mathbb{F}$ -adapted continuous processes $Y = (Y_s)_{s \in [t, T]}$ with $\mathbb{E}[\sup_{s \in [t, T]} |Y_s|^2] < \infty$.

Hypothesis 2.1. *The couple of coefficients (σ, b) belongs to $C_b^{1,1}(\mathbb{R}^d \times \mathcal{P}_2(\mathbb{R}^d) \rightarrow \mathbb{R}^{d \times d} \times \mathbb{R}^d)$, i.e., the components $\sigma_{i,j}, b_j$, $1 \leq i, j \leq d$, satisfy the following conditions:*

- i) $\sigma_{i,j}(x, \cdot), b_j(x, \cdot)$ belong to $C_b^{1,1}(\mathcal{P}_2(\mathbb{R}^d))$, for all $x \in \mathbb{R}^d$
- ii) $\sigma_{i,j}(\cdot, \mu), b_j(\cdot, \mu)$ belong to $C_b^1(\mathbb{R}^d)$, for all $\mu \in \mathcal{P}_2(\mathbb{R}^d)$
- iii) The derivatives $\partial_x \sigma_{i,j}, \partial_x b_j : \mathbb{R}^d \times \mathcal{P}_2(\mathbb{R}^d) \rightarrow \mathbb{R}^d$, $\partial_\mu \sigma_{i,j}, \partial_\mu b_j : \mathbb{R}^d \times \mathcal{P}_2(\mathbb{R}^d) \times \mathbb{R}^d \rightarrow \mathbb{R}^d$, are bounded and Lipschitz continuous.

Hypothesis 2.2. *The couple of coefficient (σ, b) belongs to $C_b^{2,1}(\mathbb{R}^d \times \mathcal{P}_2(\mathbb{R}^d) \rightarrow \mathbb{R}^{d \times d} \times \mathbb{R}^d)$, i.e., $(\sigma, b) \in C_b^{1,1}(\mathbb{R}^d \times \mathcal{P}_2(\mathbb{R}^d) \rightarrow \mathbb{R}^{d \times d} \times \mathbb{R}^d)$ and the components $\sigma_{i,j}, b_j$, $1 \leq i, j \leq d$, satisfies the following conditions:*

- i) $\partial_{x_k} \sigma_{i,j}(\cdot, \cdot), \partial_{x_k} b_j(\cdot, \cdot)$ belong to $C_b^{1,1}(\mathbb{R}^d \times \mathcal{P}_2(\mathbb{R}^d))$, for all $1 \leq k \leq d$;
- ii) $\partial_\mu \sigma_{i,j}(\cdot, \cdot, \cdot), \partial_\mu b_j(\cdot, \cdot, \cdot)$ belong to $C_b^{1,1}(\mathbb{R}^d \times \mathcal{P}_2(\mathbb{R}^d) \times \mathbb{R}^d)$, for all $\mu \in \mathcal{P}_2(\mathbb{R}^d)$
- iii) All the derivatives of $\sigma_{i,j}, b_j$, up to order 2 are bounded and Lipschitz continuous.

The following theorem is taken from [7]. It gives the Itô formula related to a probability measure.

Theorem 2.5. *Let $\Phi \in C_b^{2,1}(\mathbb{R}^d \times \mathcal{P}_2(\mathbb{R}^d))$. Then, under Hypothesis 2.2, for all $0 \leq t \leq s \leq T, x \in \mathbb{R}^d, \xi \in L^2(\mathcal{F}_t; \mathbb{R}^d)$ the Itô formula is satisfied as follow:*

$$\begin{aligned} & \Phi(X_s^{t, x, P_\xi}, P_{X_s^{t, \xi}}) - \Phi(x, P_\xi) \\ &= \int_t^s \left(\sum_{i=1}^d \partial_{x_i} \Phi(X_r^{t, x, P_\xi}, P_{X_r^{t, \xi}}) b_i(X_r^{t, x, P_\xi}, P_{X_r^{t, \xi}}) \right. \\ & \quad \left. + \frac{1}{2} \sum_{i,j,k=1}^d \partial_{x_i, x_j}^2 \Phi(X_r^{t, x, P_\xi}, P_{X_r^{t, \xi}}) (\sigma_{i,k} \sigma_{j,k})(X_r^{t, x, P_\xi}, P_{X_r^{t, \xi}}) \right. \\ & \quad \left. + \mathbb{E}' \left[\sum_{i=1}^d (\partial_\mu \Phi)_i(X_r^{t, x, P_\xi}, P_{X_r^{t, \xi}}, (X_r^{t, \xi})') b_i((X_r^{t, \xi})', P_{X_r^{t, \xi}}) \right] \right) dr \end{aligned}$$

$$\begin{aligned}
& + \frac{1}{2} \sum_{i,j,k=1}^d \partial_{y_i} ((\partial_\mu \Phi)_j (X_r^{t,x,P_\xi}, P_{X_r^{t,\xi}}, (X_r^{t,\xi})') (\sigma_{i,k} \sigma_{j,k}) ((X_r^{t,\xi})', P_{X_r^{t,\xi}})) dr \\
& + \int_t^s \sum_{i,j=1}^d \partial_{x_i} \Phi (X_r^{t,x,P_\xi}, P_{X_r^{t,\xi}}) \sigma_{i,j} (X_r^{t,x,P_\xi}, P_{X_r^{t,\xi}}) dB_r^j, \quad s \in [t, T]. \quad (11)
\end{aligned}$$

For simplicity, we will make use of the following notations concerning matrices. We denote by $\mathbb{R}^{n \times d}$ the space of real matrices of $n \times d$ -type, and by $\mathbb{R}_d^{n \times n}$ the linear space of the vectors of matrices $M = (M_1, \dots, M_d)$, with $M_i \in \mathbb{R}^{n \times n}$, $1 \leq i \leq d$. Given any $\alpha, \beta \in \mathbb{R}^n$, $L, S \in \mathbb{R}^{n \times d}$, $\gamma \in \mathbb{R}^d$ and $M, N \in \mathbb{R}_d^{n \times n}$, we introduce the following notation: $\alpha\beta = \sum_{i=1}^n \alpha_i \beta_i \in \mathbb{R}$, $\alpha \times \beta = (\alpha_i \beta_j)_{1 \leq i, j \leq n}$; $LS = \sum_{i=1}^d L_i S_i \in \mathbb{R}$, where $L = (L_1, \dots, L_d)$, $S = (S_1, \dots, S_d)$; $ML = \sum_{i=1}^d M_i L_i \in \mathbb{R}^n$; $M\alpha\gamma = \sum_{i=1}^d (M_i \alpha) \gamma_i \in \mathbb{R}^n$; $MN = \sum_{i=1}^d M_i N_i \in \mathbb{R}^{n \times n}$.

For mean-field type SDE and BSDE, we have still to introduce some notations. Let $(\tilde{\Omega}, \tilde{\mathcal{F}}, \tilde{P})$, $(\bar{\Omega}, \bar{\mathcal{F}}, \bar{P})$ be two copies of the probability space $(\Omega, \mathcal{F}, P)$. For any random variable ξ over $(\Omega, \mathcal{F}, P)$, we denote by $\tilde{\xi}$ and $\bar{\xi}$ its copies on $\tilde{\Omega}$ and $\bar{\Omega}$, respectively, which means that they have the same law as ξ , but defined over $(\tilde{\Omega}, \tilde{\mathcal{F}}, \tilde{P})$ and $(\bar{\Omega}, \bar{\mathcal{F}}, \bar{P})$. $\tilde{\mathbb{E}}[\cdot] = \int_{\tilde{\Omega}} (\cdot) d\tilde{P}$ and $\bar{\mathbb{E}}[\cdot] = \int_{\bar{\Omega}} (\cdot) d\bar{P}$ act only over the variables from $\tilde{\omega}$ and $\bar{\omega}$, respectively.

3. Formulation of the singular optimal stochastic control problem and the main result. In this section, we formulate our generalized mean-field optimal control problem and state the main result of this article. Let $(\Omega, \mathcal{F}, P)$ be a probability space with filtration $\mathcal{F}_t$. Suppose that B_t is a Brownian motion on $(\Omega, \mathcal{F}, P)$, where $\mathcal{F}$ is the filtration generated by B_t , augmented by all P -null sets. Let $\mathcal{U}$ denote the admissible control set consisting of $\mathcal{F}_t$ -adapted process u_t , take values in U , such that $\sup_{0 \leq t \leq T} \mathbb{E}|u_t|^8 < \infty$, where U is a subset of $\mathbb{R}^k$. Let $b : [0, T] \times \mathbb{R}^n \times \mathcal{P}_2(\mathbb{R}^n) \times \bar{U} \rightarrow \mathbb{R}^n$, $\sigma : [0, T] \times \mathbb{R}^n \times \mathcal{P}_2(\mathbb{R}^n) \rightarrow \mathbb{R}^{n \times d}$, $h : [0, T] \times \mathbb{R}^n \times \mathcal{P}_2(\mathbb{R}^n) \times U \rightarrow \mathbb{R}$, and $\Phi : \mathbb{R}^n \times \mathcal{P}_2(\mathbb{R}^n) \rightarrow \mathbb{R}$.

The state equation and the cost functional are defined by (1) and (2). Throughout this paper, we make the following assumptions on the coefficients:

- Hypothesis 3.1.** (1) The functions b, σ, h, Φ are differentiable with respect to (x, μ, v) . b, σ satisfy Lipschitz condition with respect to (x, μ, v) .
(2) The first-order derivatives with respect to (x, μ) of b, σ are Lipschitz continuous and bounded.
(3) The first-order derivatives with respect to (x, μ) of h, Φ are Lipschitz continuous and bounded by $C(1 + |x| + |v|)$.
(4) The second-order derivatives with respect to (x, μ) of b, σ, h, Φ are continuous and bounded. All the second-order derivatives are Borel measurable with respect to (t, x, μ, v) .

Suppose that u is an optimal control and X^u is the associated trajectory. We are to find the necessary conditions satisfied by u . Firstly, we introduce the following abbreviations:

$$\begin{aligned}
b(t) &:= b(t, X_t^u, P_{X_t^u}, u_t), \quad b_x(t) := b_x(t, X_t^u, P_{X_t^u}, u_t), \\
\tilde{b}(t) &:= b(t, \tilde{X}_t^u, P_{\tilde{X}_t^u}, \tilde{u}_t), \quad \tilde{b}_x(t) := b_x(t, \tilde{X}_t^u, P_{\tilde{X}_t^u}, \tilde{u}_t), \\
b_{xx}(t) &:= b_{xx}(t, X_t^u, P_{X_t^u}, u_t), \quad b_\mu(t) := b_\mu(t, X_t^u, P_{X_t^u}, \tilde{X}_t^u, u_t),
\end{aligned}$$

$$\begin{aligned}
\tilde{b}_\mu(t) &:= b_\mu(t, \tilde{X}_t^u, P_{\tilde{X}_t^u}, X_t^u, \tilde{u}_t), \quad b_{\mu\mu}(t) := b_{\mu\mu}(t, X_t^u, P_{X_t^u}, \tilde{X}_t^u, \tilde{X}_t^u, u_t), \\
\tilde{\tilde{b}}_{\mu\mu}(t) &:= b_{\mu\mu}(t, \tilde{X}_t^u, P_{\tilde{X}_t^u}, \tilde{X}_t^u, X_t^u, \tilde{u}_t), \quad b_{x\mu}(t) := b_{x\mu}(t, X_t^u, P_{X_t^u}, \tilde{X}_t^u, u_t), \\
b_{y\mu}(t) &:= b_{y\mu}(t, X_t^u, P_{X_t^u}, \tilde{X}_t^u, u_t), \quad \Delta b(t; v) := b(t, X_t^u, P_{X_t^u}, v) - b(t), \\
\Delta b_x(t; v) &:= b_x(t, X_t^u, P_{X_t^u}, v) - b_x(t), \quad \Delta b_\mu(t; v) := b_\mu(t, X_t^u, P_{X_t^u}, \tilde{X}_t^u, v) - b_\mu(t),
\end{aligned}$$

Similar shorthand notations for the second-order derivatives and those about σ, h can also be introduced.

Consider the first order adjoint process

$$\begin{cases} -dp_t &= \left\{ b_x(t)p_t + \sigma_x(t)q_t + h_x(t) \right. \\ &\quad \left. + \tilde{\mathbb{E}} \left[\tilde{b}_\mu(t)\tilde{p}_t + \tilde{\sigma}_\mu(t)\tilde{q}_t + \tilde{h}_\mu(t) \right] \right\} dt - q_t dB_t, \\ p_T &= \Phi_x(X_T^u, P_{X_T^u}) + \tilde{\mathbb{E}} \left[\Phi_\mu(\tilde{X}_T^u, P_{\tilde{X}_T^u}, X_T^u) \right]. \end{cases} \quad (12)$$

According to Theorem 3.1 [6], this BSDE admit a unique adapted solution. We also denote the solution as (p_t^u, q_t^u) . Define the Hamiltonian as follows:

$$H(t, x, \mu, p, q, v) = pb(t, x, \mu, v) + q\sigma(t, x, \mu) + h(t, x, \mu, v)$$

The following first-order SMP is obtained as a special case of [5].

Theorem 3.1 (The First Order SMP). *Let Hypothesis 3.1 hold. Suppose that X_t^u is the associated trajectory of the optimal control u , and (p, q) is the solution to the mean-field backward stochastic differential equation (MFBSDE) (12). Then, there is a subset $I_0 \subset [0, T]$ which is of full measure such that $\forall t \in I_0$,*

$$H(t, X_t^u, P_{X_t^u}, p_t, q_t, u_t) = \inf_{v \in \mathcal{U}} H(t, X_t^u, P_{X_t^u}, p_t, q_t, v), \quad a.s.. \quad (13)$$

As we pointed out in the introduction, the aim of this article is to derive another SMP when the Hamiltonian function above becomes singular, and hence, the SMP above is not suitable for characterizing of the optimal control u_t . To this end, we define the second-order adjoint process as follows:

$$\begin{cases} dP_t &= - \left\{ b_x^*(t)P_t + P_t b_x(t) + \tilde{\mathbb{E}} \left[\tilde{b}_\mu^*(t) \right] P_t + P_t \tilde{\mathbb{E}} \left[\tilde{b}_\mu(t) \right] \right. \\ &\quad + \sigma_x^*(t)P_t \sigma_x(t) + \tilde{\mathbb{E}} \left[\tilde{\sigma}_\mu^*(t) \right] P_t \tilde{\mathbb{E}} \left[\tilde{\sigma}_\mu(t) \right] \\ &\quad + \sigma_x^*(t)P_t \tilde{\mathbb{E}} \left[\tilde{\sigma}_\mu(t) \right] + \tilde{\mathbb{E}} \left[\tilde{\sigma}_\mu^*(t) \right] P_t \sigma_x(t) \\ &\quad + \sigma_x^*(t)Q_t + P_t \sigma_x(t) + \tilde{\mathbb{E}} \left[\tilde{\sigma}_\mu^*(t) \right] Q_t + Q_t \tilde{\mathbb{E}} \left[\tilde{\sigma}_\mu(t) \right] \\ &\quad + H_{xx}(t) + \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[\tilde{H}_{\mu\mu}(t) \right] + \tilde{\mathbb{E}} \left[\tilde{H}_{y\mu}(t) \right] + 2\tilde{\mathbb{E}} \left[\tilde{H}_{x\mu}(t) \right] \Big\} dt \\ &\quad + Q_t dB_t, \\ P_T &= 0. \end{cases} \quad (14)$$

Remark 1. By changing the terminal condition p_T , we can always eliminate the terminal cost when deducing the variational inequality. In fact, the terminal condition $P_T = 0$ is due to the assumption that $\Phi \equiv 0$. Without this assumption, we only need to set

$$\begin{aligned} P_T &= \Phi_{xx}(X_T^u, P_{X_T^u}) + 2\tilde{\mathbb{E}} \left[\Phi_{x\mu}(X_T^u, P_{X_T^u}, \tilde{X}_T^u) \right] \\ &\quad + \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[\Phi_{\mu\mu}(X_T^u, P_{X_T^u}, \tilde{X}_T^u, \tilde{X}_T^u) \right] + \tilde{\mathbb{E}} \left[\Phi_{y\mu}(X_T^u, P_{X_T^u}, \tilde{X}_T^u) \right]. \end{aligned} \quad (15)$$

Without loss of generality, we assume the terminal cost $\Phi \equiv 0$ in the following sections.

Finally, we present our main result in this article.

Theorem 3.2. *Assume that Hypothesis 3.1 hold. Let $(X^u, u.)$ be an optimal pair and let $u.$ be singular on the control region V . Suppose that (P, Q) is the unique adapted solution of equation (14). Then, there is a full measure subset $I_0 \subset [0, T]$ such that at each $t \in I_0$, $(X^u, u.)$ satisfies, not only the first-order stochastic maximum principle, but also the following inequality*

$$\begin{aligned} & \Delta H_x(t; v) \triangle b(t; v) + \tilde{\mathbb{E}} \left[\Delta H_\mu(t; v) \triangle \tilde{b}(t; v) \right] \\ & + \Delta b^*(t; v) P_t \triangle b(t; v) \geq 0, \quad \forall v \in U, a.s.. \end{aligned} \quad (16)$$

4. Quantitative analysis of the impact of control actions on the state.

In this section, we expand the state process according to different orders of the perturbation parameter $d(u, v)$, a distance between the optimal control u and its perturbation v .

Lemma 4.1. *Under Hypothesis 3.1 on the coefficients, we have,*

$$\mathbb{E} \sup_{0 \leq t \leq T} |X_t^v|^8 \leq K \left(1 + \mathbb{E} \left| \int_0^T |v_s| ds \right|^8 \right),$$

Proof. By the state equation (1), for $\tau \in [0, T]$ we have,

$$\begin{aligned} \mathbb{E} \sup_{0 \leq t \leq \tau} |X_t^v|^8 & \leq K \mathbb{E} \left(|x|^8 + \sup_{0 \leq t \leq \tau} \left| \int_0^t b(s, X_s^v, P_{X_s^v}, v_s) ds \right|^8 \right. \\ & \quad \left. + \left(\int_0^\tau |\sigma(s, X_s^v, P_{X_s^v})|^2 ds \right)^4 \right) \\ & \leq K \left(|x|^8 + \mathbb{E} \int_0^\tau \sup_{0 \leq s \leq r} |X_s^v|^8 dr + \mathbb{E} \left| \int_0^T |v_s| ds \right|^8 \right) \end{aligned} \quad (17)$$

From Gronwall's inequality, we then have the desired result. $\square$

For $v_i \in \mathcal{U}$, $i = 1, 2$, we define

$$I(v_1, v_2) = \{t \in [0, T] | P(\{\omega : v_1(t) \neq v_2(t)\}) > 0\}$$

and $d(v_1, v_2) = |I(v_1, v_2)|$ is the Lebesgue measure of $I(v_1, v_2)$. Then, $(\mathcal{U}, d)$ is a metric space.

Given the optimal pair $(X^u, u.)$, we now proceed to the perturbation X^v of X^u . Let

$$\begin{aligned} X_t^{v,1} &= \int_0^t \left\{ b_x(s) X_s^{v,1} + \tilde{\mathbb{E}} \left[b_\mu(s) \tilde{X}_s^{v,1} \right] + \Delta b(s, v) \right\} ds \\ & \quad + \int_0^t \left\{ \sigma_x(s) X_s^{v,1} + \tilde{\mathbb{E}} \left[\sigma_\mu(s) \tilde{X}_s^{v,1} \right] \right\} dB_s \\ &:= \int_0^t b^1(s, v) ds + \int_0^t \sigma^1(s, v) dB_s, \end{aligned} \quad (18)$$

and

$$\begin{aligned} X_t^{v,2} &= \int_0^t \left\{ b_x(s) X_s^{v,2} + \tilde{\mathbb{E}} \left[b_\mu(s) \tilde{X}_s^{v,2} \right] + \Delta b_x(s, v) X_s^{v,1} + \tilde{\mathbb{E}} \left[\Delta b_\mu(s, v) \tilde{X}_s^{v,1} \right] \right. \\ & \quad \left. + \frac{1}{2} b_{xx}(s) X_s^{v,1} \times X_s^{v,1} + \tilde{\mathbb{E}} \left[b_{x\mu}(s) X_s^{v,1} \times \tilde{X}_s^{v,1} \right] \right\} ds \end{aligned}$$

$$\begin{aligned}
& + \frac{1}{2} \tilde{\mathbb{E}} \left[b_{y\mu}(s) \tilde{X}_s^{v,1} \times \tilde{X}_s^{v,1} \right] + \frac{1}{2} \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[b_{\mu\mu}(s) \tilde{X}_s^{v,1} \times \tilde{X}_s^{v,1} \right] \Big\} ds \\
& + \int_0^t \left\{ \sigma_x(s) X_s^{v,2} + \tilde{\mathbb{E}} \left[\sigma_\mu(s) \tilde{X}_s^{v,2} \right] \right. \\
& + \frac{1}{2} \sigma_{xx}(s) X_s^{v,1} \times X_s^{v,1} + \tilde{\mathbb{E}} \left[\sigma_{x\mu}(s) X_s^{v,1} \times \tilde{X}_s^{v,1} \right] \\
& + \frac{1}{2} \tilde{\mathbb{E}} \left[\sigma_{y\mu}(s) \tilde{X}_s^{v,1} \times \tilde{X}_s^{v,1} \right] + \frac{1}{2} \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[\sigma_{\mu\mu}(s) \tilde{X}_s^{v,1} \times \tilde{X}_s^{v,1} \right] \Big\} dB_s \\
& := \int_0^t b^2(s, v) ds + \int_0^t \sigma^2(s, v) dB_s
\end{aligned} \tag{19}$$

Denote

$$X^{v*} := X^*(v) = X^u - X^{v,1} - X^{v,2} - X^v. \tag{20}$$

The following lemmas give the estimation of their orders according to parameter $d(v, u)$.

Lemma 4.2. *Assume that Hypothesis 3.1 holds. Then, there exists a $K > 0$, such that for any $v(\cdot), u(\cdot) \in \mathcal{U}$, we have*

$$\mathbb{E} \sup_{0 \leq t \leq T} |X_t^{v,1}|^2 \leq K d^2(v, u), \tag{21}$$

$$\mathbb{E} \sup_{0 \leq t \leq T} |X_t^{v,2}|^2 \leq K d^4(v, u). \tag{22}$$

Proof. For any $\tau \in [0, T]$, denote

$$g_1(\tau) = \mathbb{E} \sup_{0 \leq t \leq \tau} |X_t^{v,1}|^2, \quad g_2(\tau) = \mathbb{E} \sup_{0 \leq t \leq \tau} |X_t^{v,2}|^2.$$

By Hypothesis 3.1 and the Burkholder-Davis-Gundy inequality, we have

$$g_1(\tau) \leq K \left(\int_0^\tau g_1(s) ds + \mathbb{E} \left| \int_0^\tau \triangle b(s; v) |ds| \right|^2 \right), \tag{23}$$

and

$$\begin{aligned}
g_2(\tau) & \leq K \left(\int_0^\tau g_2(s) ds + [g_1(T)]^2 \right. \\
& \quad \left. + \mathbb{E} \left| \int_0^T \triangle b_x(s; v) |ds| \right|^4 + \mathbb{E} \tilde{\mathbb{E}} \left| \int_0^T \triangle b_\mu(s; v) |ds| \right|^4 \right).
\end{aligned} \tag{24}$$

The application of Grownwall's inequality allows to obtain that

$$\mathbb{E} \sup_{0 \leq t \leq T} |X_t^{v,1}|^2 \leq K \left(\mathbb{E} \left| \int_0^T \triangle b(s; v) |ds| \right|^2 \right), \tag{25}$$

$$\begin{aligned}
\mathbb{E} \sup_{0 \leq t \leq T} |X_t^{v,2}|^2 & \leq K \left(\mathbb{E} \left| \int_0^T \triangle b(s; v) |ds| \right|^4 + \mathbb{E} \left| \int_0^T \triangle b_x(s; v) |ds| \right|^4 \right. \\
& \quad \left. + \mathbb{E} \tilde{\mathbb{E}} \left| \int_0^T \triangle b_\mu(s; v) |ds| \right|^4 \right)
\end{aligned} \tag{26}$$

Notice that the first-order derivative b_x is bounded. Then, (26) implies the following estimate

$$\mathbb{E} \sup_{0 \leq t \leq T} |X_t^{v,2}|^2 \leq K \left(\mathbb{E} \left| \int_0^T |\Delta b(s; v)| ds \right|^4 + d^4(u, v) \right). \quad (27)$$

According to assumption about v and u , then,

$$\mathbb{E} \sup_{0 \leq t \leq T} |X_t^{v,1}|^2 \leq K d^2(v, u), \text{ and } \mathbb{E} \sup_{0 \leq t \leq T} |X_t^{v,2}|^2 \leq K d^4(v, u). \quad (28)$$

In fact, by Minkowski's inequality, we have

$$\begin{aligned} \mathbb{E} \left| \int_0^T |\Delta b(s; v)| ds \right|^4 &\leq \left| \int_0^T \left(\mathbb{E} |\Delta b(s; v)|^4 \right)^{\frac{1}{4}} ds \right|^4 \\ &= \left| \int_{I(u,v)} \left(\mathbb{E} |\Delta b(s; v)|^4 \right)^{\frac{1}{4}} ds \right|^4 \leq K d^4(u, v). \end{aligned} \quad (29)$$

□

The following lemma gives the order of X_t^{v*} .

Lemma 4.3. *Assume Hypothesis 3.1 holds. For $v(\cdot) \in \mathcal{U}$ and Borel subset $I_\rho \subset [0, T]$ with Lebesgue measure $|I_\rho|$, define*

$$\hat{v}_t = v_t 1_{I_\rho}(t) + u_t 1_{[0,T] \setminus I_\rho}(t), \quad X_t^{\hat{v}*} := X^*(t, \hat{v}). \quad (30)$$

Then we have

$$\mathbb{E} \sup_{0 \leq t \leq T} |X_t^{\hat{v}*}|^2 = o(|I_\rho|^4) \quad (31)$$

when $|I_\rho| \rightarrow 0$.

Proof. We introduce the following notations first

$$\begin{aligned} \Delta b_{xx}(s; \lambda \eta; v) &:= b_{xx}(s, X_s^u + \lambda \eta X_s^{v,12}, P_{X_s^u + \lambda \eta X_s^{v,12}}, v_s) - b_{xx}(s) \\ \Delta b_{\mu\mu}(s; \lambda \eta; v) &:= b_{\mu\mu}(s, X_s^u, P_{X_s^u + \lambda \eta X_s^{v,12}}, \tilde{X}_s^u + \lambda \eta \tilde{X}_s^{v,12}, \tilde{X}_s^u + \lambda \eta \tilde{X}_s^{v,12}, v_s) - b_{xx}(s), \\ \Delta b_{\mu y}(s; \lambda \eta; v) &:= b_{\mu y}(s, X_s^u, P_{X_s^u + \lambda \eta X_s^{v,12}}, \tilde{X}_s^u + \lambda \eta \tilde{X}_s^{v,12}, v_s) - b_{\mu y}(s) \\ \Delta b_{x\mu}(s; \lambda; v) &:= b_{x\mu}(s, X_s^u, P_{X_s^u + \lambda X_s^{v,12}}, \tilde{X}_s^u + \lambda \tilde{X}_s^{v,12}, v_s) - b_{x\mu}(s), \end{aligned}$$

where $X^{v,12} := X^{v,1} + X^{v,2}$. Similarly notations can be introduced with b replaced by σ .

We now proceed to estimating $X^*(\hat{v})$ defined by (20). By (1), (18) and (19), we have

$$dX_t^{\hat{v}*} = \alpha(t)dt + \beta(t)dB_t, \quad (32)$$

where

$$\begin{aligned} \alpha(t) &= b(t, X_t^{\hat{v}}, P_{X_t^{\hat{v}}}, \hat{v}_t) - [b(t) + b^1(t, \hat{v}) + b^2(t, \hat{v})], \\ \beta(t) &= \sigma(t, X_t^{\hat{v}}, P_{X_t^{\hat{v}}}) - [\sigma(t) + \sigma^1(t, \hat{v}) + \sigma^2(t, \hat{v})]. \end{aligned}$$

We can represent $\alpha(t)$ as follows.

$$\begin{aligned} \alpha(t) &= b(t, X_t^{\hat{v}}, P_{X_t^{\hat{v}}}, \hat{v}_t) - \left[b(t) + \left\{ b_x(t) X_t^{\hat{v},1} + \tilde{\mathbb{E}} \left[b_\mu(t) \tilde{X}_t^{\hat{v},1} \right] + \Delta b(t, \hat{v}) \right\} \right. \\ &\quad \left. + \left\{ b_x(t) X_t^{\hat{v},2} + \tilde{\mathbb{E}} \left[b_\mu(t) \tilde{X}_t^{\hat{v},2} \right] + \Delta b_x(t, \hat{v}) X_t^{\hat{v},1} + \tilde{\mathbb{E}} \left[\Delta b_\mu(t, \hat{v}) \tilde{X}_t^{\hat{v},1} \right] \right\} \right] \end{aligned}$$

$$\begin{aligned}
& + \frac{1}{2} b_{xx}(t) X_t^{\hat{v},1} \times X_t^{\hat{v},1} + \tilde{\mathbb{E}} \left[b_{x\mu}(t) X_t^{\hat{v},1} \times \tilde{X}_t^{\hat{v},1} \right] \\
& + \frac{1}{2} \tilde{\mathbb{E}} \left[b_{y\mu}(t) \tilde{X}_t^{\hat{v},1} \times \tilde{X}_t^{\hat{v},1} \right] + \frac{1}{2} \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[b_{\mu\mu}(t) \tilde{X}_t^{\hat{v},1} \times \tilde{X}_t^{\hat{v},1} \right] \Big\}.
\end{aligned} \tag{33}$$

Denote

$$\begin{aligned}
A(t; \hat{v}) &= \frac{1}{2} b_{xx}(t) (X_t^{\hat{v},2} \times X_t^{\hat{v},2} + 2X_t^{\hat{v},1} \times X_t^{\hat{v},2}) \\
&+ \frac{1}{2} \tilde{\mathbb{E}} \left[b_{yy}(t) (\tilde{X}_t^{\hat{v},2} \times \tilde{X}_t^{\hat{v},2} + 2\tilde{X}_t^{\hat{v},1} \times \tilde{X}_t^{\hat{v},2}) \right] \\
&+ \frac{1}{2} \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[b_{\mu\mu}(t) (\tilde{X}_t^{\hat{v},2} \times \tilde{X}_t^{\hat{v},2} + \tilde{X}_t^{\hat{v},1} \times \tilde{X}_t^{\hat{v},2} + \tilde{X}_t^{\hat{v},1} \times \tilde{X}_t^{\hat{v},2}) \right] \\
&+ \triangle b_x(t; \hat{v}) X_t^{\hat{v},2} + \tilde{\mathbb{E}} \left[\triangle b_\mu(t; \hat{v}) \tilde{X}_t^{\hat{v},2} \right] \\
&+ \tilde{\mathbb{E}} \left[b_{x\mu}(t) (X_t^{\hat{v},2} \times \tilde{X}_t^{\hat{v},2} + X_t^{\hat{v},1} \times \tilde{X}_t^{\hat{v},2} + \tilde{X}_t^{\hat{v},1} \times X_t^{\hat{v},2}) \right] \\
&+ \int_0^1 \int_0^1 \lambda \left[\triangle b_{xx}(t; \lambda\eta; \hat{v}) d\lambda d\eta X_t^{\hat{v},12} \times X_t^{\hat{v},12} \right] \\
&+ \int_0^1 \int_0^1 \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[\lambda (\triangle b_{\mu\mu}(t; \lambda\eta; \hat{v}) d\lambda d\eta \tilde{X}_t^{\hat{v},12} \times \tilde{X}_t^{\hat{v},12}) \right] \\
&+ \int_0^1 \int_0^1 \tilde{\mathbb{E}} \left[\lambda (\triangle b_{\mu y}(t; \lambda\eta; \hat{v}) d\lambda d\eta \tilde{X}_t^{\hat{v},12} \times \tilde{X}_t^{\hat{v},12}) \right] \\
&+ \tilde{\mathbb{E}} \left[\int_0^1 \triangle b_{x\mu}(t; \lambda; \hat{v}) d\lambda X_t^{\hat{v},12} \times \tilde{X}_t^{\hat{v},12} \right].
\end{aligned} \tag{34}$$

It is easy to show that

$$\begin{aligned}
\alpha(t) &= b(t, X_t^{\hat{v}}, P_{X_t^{\hat{v}}}, \hat{v}_t) - \left[b(t, X_t^u, P_{X_t^u + X_t^{\hat{v},12}}, \hat{v}_t) \right. \\
&\quad \left. + b_x(t, X_t^u, P_{X_t^u + X_t^{\hat{v},12}}, \hat{v}_t) X_t^{\hat{v},12} \right. \\
&\quad \left. + \int_0^1 \int_0^1 \lambda b_{xx}(t, X_t^u + \lambda\eta X_t^{\hat{v},12}, P_{X_t^u + X_t^{\hat{v},12}}, \hat{v}_t) d\lambda d\eta X_t^{\hat{v},12} \times X_t^{\hat{v},12} \right] \\
&\quad + A(t; \hat{v}) \\
&= b(t, X_t^{\hat{v}}, P_{X_t^{\hat{v}}}, \hat{v}_t) - b(t, X_t^u + X_t^{\hat{v},12}, P_{X_t^u + X_t^{\hat{v},12}}, \hat{v}_t) + A(t; \hat{v}).
\end{aligned}$$

Similarly, by setting

$$\begin{aligned}
B(t; \hat{v}) &:= \frac{1}{2} \sigma_{xx}(t) (X_t^{\hat{v},2} \times X_t^{\hat{v},2} + 2X_t^{\hat{v},1} \times X_t^{\hat{v},2}) \\
&+ \frac{1}{2} \tilde{\mathbb{E}} \left[\sigma_{yy}(t) (\tilde{X}_t^{\hat{v},2} \times \tilde{X}_t^{\hat{v},2} + 2\tilde{X}_t^{\hat{v},1} \times \tilde{X}_t^{\hat{v},2}) \right] \\
&+ \frac{1}{2} \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[\sigma_{\mu\mu}(t) (\tilde{X}_t^{\hat{v},2} \times \tilde{X}_t^{\hat{v},2} + \tilde{X}_t^{\hat{v},1} \times \tilde{X}_t^{\hat{v},2} + \tilde{X}_t^{\hat{v},1} \times \tilde{X}_t^{\hat{v},2}) \right] \\
&+ \tilde{\mathbb{E}} \left[\sigma_{x\mu}(t) (X_t^{\hat{v},2} \times \tilde{X}_t^{\hat{v},2} + X_t^{\hat{v},1} \times \tilde{X}_t^{\hat{v},2} + \tilde{X}_t^{\hat{v},1} \times X_t^{\hat{v},2}) \right] \\
&+ \int_0^1 \int_0^1 \lambda \left[\triangle \sigma_{xx}(t; \lambda\eta; \hat{v}) d\lambda d\eta X_t^{\hat{v},12} \times X_t^{\hat{v},12} \right] \\
&+ \int_0^1 \int_0^1 \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[\lambda \triangle \sigma_{\mu\mu}(t; \lambda\eta; \hat{v}) d\lambda d\eta \tilde{X}_t^{\hat{v},12} \times \tilde{X}_t^{\hat{v},12} \right]
\end{aligned}$$

$$\begin{aligned}
& + \int_0^1 \int_0^1 \tilde{\mathbb{E}} \left[\lambda \triangle \sigma_{\mu y}(t; \lambda \eta; \hat{v}) d\lambda d\eta \tilde{X}_t^{\hat{v},12} \times \tilde{X}_t^{\hat{v},12} \right] \\
& + \tilde{\mathbb{E}} \left[\int_0^1 (\triangle \sigma_{x\mu}(t; \lambda; \hat{v}) d\lambda X_t^{\hat{v},12} \times \tilde{X}_t^{\hat{v},12}) d\lambda X_t^{\hat{v},12} \times \tilde{X}_t^{\hat{v},12} \right], \quad (35)
\end{aligned}$$

we have

$$\begin{aligned}
\beta(t) &= \sigma(t, X_t^{\hat{v}}, P_{X_t^{\hat{v}}}) - \left[\sigma(t, X_t^u, P_{X_t^u + X_t^{\hat{v},12}}) + \sigma_x(t, X_t^u, P_{X_t^u + X_t^{\hat{v},12}}) X_t^{\hat{v},12} \right. \\
& \quad \left. + \int_0^1 \int_0^1 \lambda \sigma_{xx}(t, X_t^u + \lambda \eta X_t^{\hat{v},12}, P_{X_t^u + X_t^{\hat{v},12}}) d\lambda d\eta X_t^{\hat{v},12} \times X_t^{\hat{v},12} \right] \\
& \quad + B(t; \hat{v}) \\
&= \sigma(t, X_t^{\hat{v}}, P_{X_t^{\hat{v}}}) - \sigma(t, X_t^u + X_t^{\hat{v},12}, P_{X_t^u + X_t^{\hat{v},12}}) + B(t; \hat{v}).
\end{aligned}$$

According to Hypothesis 3.1, we have

$$\begin{aligned}
& \left| b(t, X_t^{\hat{v}}, P_{X_t^{\hat{v}}}, \hat{v}_t) - b(t, X_t^u + X_t^{\hat{v},12}, P_{X_t^u + X_t^{\hat{v},12}}, \hat{v}_t) \right| \\
& \leq K \left(|X_t^{\hat{v}*}| + W_2(P_{X_t^{\hat{v}}}, P_{X_t^u + X_t^{\hat{v},12}}) \right).
\end{aligned}$$

Note that

$$W_2(P_{X_s^{\hat{v}}}, P_{X_s^u + X_s^{\hat{v},12}})^2 \leq \mathbb{E} |X_s^{\hat{v}} - X_s^u - X_s^{\hat{v},12}|^2 = \mathbb{E} |X_s^{\hat{v}*}|^2.$$

By Burkholder-Davis-Gundy inequality, for $\tau \in [0, T]$, we obtain the following estimation

$$\begin{aligned}
\mathbb{E} \sup_{0 \leq t \leq \tau} |X_t^{\hat{v}*}|^2 & \leq \int_0^\tau K \mathbb{E} \sup_{0 \leq r \leq s} |X_r^{\hat{v}*}|^2 ds + \mathbb{E} \int_0^\tau |A(s; \hat{v})|^2 ds \\
& \quad + \mathbb{E} \int_0^\tau |B(s; \hat{v})|^2 ds. \quad (36)
\end{aligned}$$

According to Gronwall's inequality, we have

$$\mathbb{E} \sup_{0 \leq t \leq T} |X_t^{\hat{v}*}|^2 \leq K \left(\mathbb{E} \int_0^T |A(s; \hat{v})|^2 ds + \mathbb{E} \int_0^T |B(s; \hat{v})|^2 ds \right). \quad (37)$$

About $A(s; \hat{v})$ we have

$$\begin{aligned}
& \mathbb{E} \int_0^T |A(s; \hat{v})|^2 ds \\
& \leq K \mathbb{E} \left(\sup_{0 \leq s \leq t} |X_s^{\hat{v},2}|^4 + \sup_{0 \leq s \leq t} |X_s^{\hat{v},1}|^2 \sup_{0 \leq s \leq t} |X_s^{\hat{v},2}|^2 \right. \\
& \quad \left. + \sup_{0 \leq s \leq t} |X_s^{\hat{v},2}|^2 \int_0^T \left[|\triangle b_x(s; \hat{v})|^2 + |\triangle b_\mu(s; \hat{v})|^2 \right] ds \right. \\
& \quad \left. + \sup_{0 \leq s \leq t} |X_s^{\hat{v},1}|^4 \int_0^T \int_0^1 \int_0^1 |\lambda \triangle b_{xx}(s; \lambda \eta; \hat{v})|^2 d\lambda d\eta ds \right. \\
& \quad \left. + \sup_{0 \leq s \leq t} |X_s^{\hat{v},1}|^4 \int_0^T \int_0^1 \int_0^1 \tilde{\mathbb{E}} \tilde{\mathbb{E}} |\lambda \triangle b_{\mu\mu}(s; \lambda \eta; \hat{v})|^2 \cdot d\lambda d\eta ds \right. \\
& \quad \left. + \sup_{0 \leq s \leq t} |X_s^{\hat{v},1}|^4 \int_0^T \int_0^1 \int_0^1 \tilde{\mathbb{E}} |\lambda \triangle b_{\mu y}(s; \lambda \eta; \hat{v})|^2 d\lambda d\eta ds \right)
\end{aligned}$$

$$+ \sup_{0 \leq s \leq t} |X_s^{\hat{v},1}|^4 \tilde{\mathbb{E}} \int_0^T \int_0^1 |\Delta b_{x\mu}(s; \lambda; \hat{v})|^2 d\lambda ds \Big). \quad (38)$$

Note that

$$\mathbb{E} \left| \int_0^T |\Delta b(s; \hat{v})| ds \right|^8 \leq K |I_\rho|^8,$$

similar estimates hold with b replaced by b_x and b_μ . Since $X_t^{\hat{v},12} \rightarrow 0$ as $|I_\rho| \rightarrow 0$, so we also have

$$\Delta b_{xx}(s; \lambda\eta; \hat{v}) \rightarrow 0,$$

replace b_{xx} by $b_{\mu\mu}$, $b_{\mu y}$ and $b_{x\mu}$, we can get the similar result when $|I_\rho| \rightarrow 0$.

According to estimation of $X^{\hat{v},1}$, $X^{\hat{v},2}$ in Lemma 4.2, we obtain

$$\begin{aligned} & \mathbb{E} \int_0^T |A(s; \hat{v})|^2 ds \\ \leq & K \left(\sqrt{\mathbb{E} \left| \int_0^T |\Delta b(s; \hat{v})| ds \right|^8} + \sqrt{\mathbb{E} \left| \int_0^T |\Delta b_x(s; \hat{v})| ds \right|^8} \right. \\ & + \sqrt{\mathbb{E} \tilde{\mathbb{E}} \left| \int_0^T |\Delta b_\mu(s; \hat{v})| ds \right|^8} \Big) \times \left(\sqrt{\mathbb{E} \left| \int_0^T |\Delta b(s; \hat{v})| ds \right|^8} \right. \\ & + \sqrt{\mathbb{E} \left| \int_0^T |\Delta b_x(s; \hat{v})| ds \right|^8} + \sqrt{\mathbb{E} \tilde{\mathbb{E}} \left| \int_0^T |\Delta b_\mu(s; \hat{v})| ds \right|^8} \\ & + \sqrt{\mathbb{E} \int_0^T |\Delta b(s; \hat{v})|^8 ds} + \sqrt{\mathbb{E} \int_0^T |\Delta b_x(s; \hat{v})|^4 ds} \\ & + \sqrt{\mathbb{E} \tilde{\mathbb{E}} \int_0^T |\Delta b_\mu(s; \hat{v})|^4 ds} + \sqrt{\mathbb{E} \int_0^T \int_0^1 \int_0^1 |\lambda \Delta b_{xx}(s; \lambda\eta; \hat{v})|^4 d\lambda d\eta ds} \\ & + \sqrt{\mathbb{E} \tilde{\mathbb{E}} \int_0^T \int_0^1 \int_0^1 |\lambda \Delta b_{\mu\mu}(s; \lambda\eta; \hat{v})|^4 d\lambda d\eta ds} \\ & + \sqrt{\mathbb{E} \tilde{\mathbb{E}} \int_0^T \int_0^1 \int_0^1 |\lambda \Delta b_{\mu y}(s; \lambda\eta; \hat{v})|^4 d\lambda d\eta ds} \\ & + \sqrt{\mathbb{E} \tilde{\mathbb{E}} \int_0^T \int_0^1 |\lambda \Delta b_{x\mu}(s; \lambda; \hat{v})|^4 d\lambda ds} \Big) = o(|I_\rho|^4), \text{ as } |I_\rho| \rightarrow 0. \quad (39) \end{aligned}$$

Similarly

$$\mathbb{E} \int_0^T |B(s; \hat{v})|^2 ds = o(|I_\rho|^4), \text{ as } |I_\rho| \rightarrow 0. \quad (40)$$

Finally, by (37) we have the desire result. $\square$

5. Expansion of the cost functional with respect to control variable. In this section, we use the method of Lemma 4.3 again to study the expansion of the cost functional according to different order of the perturbation.

Lemma 5.1. *Assume that Hypothesis 3.1 holds. Define*

$$\begin{aligned}
J^*(v.) &= J(v.) - J(u.) - \mathbb{E} \int_0^t \left\{ h_x(s) X_s^{v,1} + \tilde{\mathbb{E}} \left[h_\mu(s) \tilde{X}_s^{v,1} \right] + \Delta h(s, v) \right. \\
&\quad + h_x(s) X_s^{v,2} + \tilde{\mathbb{E}} \left[h_\mu(s) \tilde{X}_s^{v,2} \right] + \Delta h_x(s, v) X_s^{v,1} + \tilde{\mathbb{E}} \left[\Delta h_\mu(s, v) \tilde{X}_s^{v,1} \right] \\
&\quad + \frac{1}{2} h_{xx}(s) X_s^{v,1} \times X_s^{v,1} + \tilde{\mathbb{E}} \left[h_{x\mu}(s) X_s^{v,1} \times \tilde{X}_s^{v,1} \right] \\
&\quad \left. + \frac{1}{2} \tilde{\mathbb{E}} \left[h_{y\mu}(s) \tilde{X}_s^{v,1} \times \tilde{X}_s^{v,1} \right] + \frac{1}{2} \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[h_{\mu\mu}(s) \tilde{X}_s^{v,1} \times \bar{X}_s^{v,1} \right] \right\} ds. \quad (41)
\end{aligned}$$

Recall that $\hat{v}$ is defined by (30) by I_ρ . Then, when $|I_\rho| \rightarrow 0$, we have

$$J^*(\hat{v}.) = o(|I_\rho|^2). \quad (42)$$

Proof. Denote

$$Y_t^v = \int_0^t h(s, X_s^v, P_{X_s^v}, v_s) ds. \quad (43)$$

By (20) and Lemma 4.3, we have

$$Y_t^v = Y_t^u + Y_t^{v,1} + Y_t^{v,2} + Y_t^{v*}, \quad (44)$$

where

$$Y_t^v = \int_0^t h(s, X_s^v, P_{X_s^v}, v_s) ds, \quad (45)$$

$$Y_t^{v,1} = \int_0^t \left\{ h_x(s) X_s^{v,1} + \tilde{\mathbb{E}} \left[h_\mu(s) \tilde{X}_s^{v,1} \right] + \Delta h(s, v) \right\} ds, \quad (46)$$

$$\begin{aligned}
Y_t^{v,2} &= \int_0^t \left\{ h_x(s) X_s^{v,2} + \tilde{\mathbb{E}} \left[h_\mu(s) \tilde{X}_s^{v,2} \right] + \Delta h_x(s, v) X_s^{v,1} + \tilde{\mathbb{E}} [\Delta h_\mu(s, v) \tilde{X}_s^{v,1}] \right. \\
&\quad + \frac{1}{2} h_{xx}(s) X_s^{v,1} \times X_s^{v,1} + \tilde{\mathbb{E}} \left[h_{x\mu}(s) X_s^{v,1} \times \tilde{X}_s^{v,1} \right] \\
&\quad \left. + \frac{1}{2} \tilde{\mathbb{E}} \left[h_{y\mu}(s) \tilde{X}_s^{v,1} \times \tilde{X}_s^{v,1} \right] + \frac{1}{2} \tilde{\mathbb{E}} \tilde{\mathbb{E}} [h_{\mu\mu}(s) \tilde{X}_s^{v,1} \times \bar{X}_s^{v,1}] \right\} ds. \quad (47)
\end{aligned}$$

Then,

$$J(v.) - J(u.) = \mathbb{E} Y_T^v - \mathbb{E} Y_T^u, \quad (48)$$

and hence,

$$J^*(\hat{v}.) = \mathbb{E} Y_T^v - \mathbb{E} Y_T^u - \mathbb{E} Y_T^{v,1} - \mathbb{E} Y_T^{v,2}. \quad (49)$$

Using the same method in Lemma 4.3, we complete the proof. $\square$

Now, we proceed to deriving the expansion of the perturbed cost function.

$$\begin{aligned}
X_t^{v,12} &= \int_0^t \left\{ b_x(s) X_s^{v,1} + \tilde{\mathbb{E}} \left[b_\mu(s) \tilde{X}_s^{v,1} \right] + \Delta b(s, v) \right. \\
&\quad + b_x(s) X_s^{v,2} + \tilde{\mathbb{E}} \left[b_\mu(s) \tilde{X}_s^{v,2} \right] + \Delta b_x(s, v) X_s^{v,1} + \tilde{\mathbb{E}} \left[\Delta b_\mu(s, v) \tilde{X}_s^{v,1} \right] \\
&\quad + \frac{1}{2} b_{xx}(s) X_s^{v,1} \times X_s^{v,1} + \tilde{\mathbb{E}} \left[b_{x\mu}(s) X_s^{v,1} \times \tilde{X}_s^{v,1} \right] \\
&\quad \left. + \frac{1}{2} \tilde{\mathbb{E}} \left[b_{y\mu}(s) \tilde{X}_s^{v,1} \times \tilde{X}_s^{v,1} \right] + \frac{1}{2} \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[b_{\mu\mu}(s) \tilde{X}_s^{v,1} \times \bar{X}_s^{v,1} \right] \right\} ds
\end{aligned}$$

$$\begin{aligned}
& + \int_0^t \left\{ \sigma_x(s) X_s^{v,1} + \tilde{\mathbb{E}} \left[\sigma_\mu(s) \tilde{X}_s^{v,1} \right] + \sigma_x(s) X_s^{v,2} + \tilde{\mathbb{E}} \left[\sigma_\mu(s) \tilde{X}_s^{v,2} \right] \right. \\
& + \frac{1}{2} \sigma_{xx}(s) X_s^{v,1} \times X_s^{v,1} + \tilde{\mathbb{E}} \left[\sigma_{x\mu}(s) X_s^{v,1} \times \tilde{X}_s^{v,1} \right] \\
& \left. + \frac{1}{2} \tilde{\mathbb{E}} \left[\sigma_{y\mu}(s) \tilde{X}_s^{v,1} \times \tilde{X}_s^{v,1} \right] + \frac{1}{2} \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[\sigma_{\mu\mu}(s) \tilde{X}_s^{v,1} \times \bar{X}_s^{v,1} \right] \right\} dB_s. \quad (50)
\end{aligned}$$

Recalling that p_t is given by (12) and applying Itô's formula to $p_t X_t^{v,12}$, we obtain

$$\begin{aligned}
& \mathbb{E} \int_0^T \left\{ h_x(s) X_s^{v,12} + \tilde{\mathbb{E}} \left[h_\mu(s) \tilde{X}_s^{v,12} \right] \right\} ds \\
= & \mathbb{E} \int_0^T p(s) \left\{ \Delta b(s; v) + \Delta b_x(s; v) X_s^{v,1} + \tilde{\mathbb{E}} \left[\Delta b_\mu(s; v) \tilde{X}_s^{v,1} \right] \right. \\
& + \frac{1}{2} b_{xx}(s) X_s^{v,1} \times X_s^{v,1} + \tilde{\mathbb{E}} \left[b_{x\mu}(s) X_s^{v,1} \times \tilde{X}_s^{v,1} \right] \\
& + \frac{1}{2} \tilde{\mathbb{E}} \left[b_{y\mu}(s) \tilde{X}_s^{v,1} \times \tilde{X}_s^{v,1} \right] + \frac{1}{2} \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[b_{\mu\mu}(s) \tilde{X}_s^{v,1} \times \bar{X}_s^{v,1} \right] \left. \right\} ds \\
& + \mathbb{E} \int_0^T q(s) \left\{ \frac{1}{2} \sigma_{xx}(s) X_s^{v,1} \times X_s^{v,1} + \tilde{\mathbb{E}} \left[\sigma_{x\mu}(s) X_s^{v,1} \times \tilde{X}_s^{v,1} \right] \right. \\
& \left. + \frac{1}{2} \tilde{\mathbb{E}} \left[\sigma_{y\mu}(s) \tilde{X}_s^{v,1} \times \tilde{X}_s^{v,1} \right] + \frac{1}{2} \tilde{\mathbb{E}} \tilde{\mathbb{E}} \left[\sigma_{\mu\mu}(s) \tilde{X}_s^{v,1} \times \bar{X}_s^{v,1} \right] \right\} ds. \quad (51)
\end{aligned}$$

Hence,

$$\begin{aligned}
& J(v) - J(u) \\
= & \mathbb{E} \int_0^T \Delta H(s; v) ds + \mathbb{E} \int_0^T \Delta H_x(s; v) X_s^{v,1} ds \\
& + \mathbb{E} \tilde{\mathbb{E}} \int_0^T \Delta H_\mu(s; v) \tilde{X}_s^{v,1} ds \\
& + \frac{1}{2} \mathbb{E} \int_0^T \text{Trace} \left\{ H_{xx}(s) X_s^{v,1} X_s^{*v,1} \right\} ds \\
& + \mathbb{E} \tilde{\mathbb{E}} \int_0^T \text{Trace} \left\{ H_{x\mu}(s) X_s^{v,1} \tilde{X}_s^{*v,1} \right\} ds \\
& + \frac{1}{2} \mathbb{E} \tilde{\mathbb{E}} \int_0^T \text{Trace} \left\{ H_{y\mu}(s) \tilde{X}_s^{v,1} \tilde{X}_s^{*v,1} \right\} ds \\
& + \frac{1}{2} \mathbb{E} \tilde{\mathbb{E}} \int_0^T \text{Trace} \left\{ H_{\mu\mu}(s) \tilde{X}_s^{v,1} \bar{X}_s^{*v,1} \right\} ds + J^*(v(\cdot)). \quad (52)
\end{aligned}$$

Now we apply the range theorem for vector-valued measures due to [18], to deduce the variational inequality.

Recall that $\hat{v}_t$ is defined by (30). According to Lemma 4.1 [18], for any $0 < \rho < 1$, we can choose a suitable $I_\rho \subset [0, T]$ such that $|I_\rho| = \rho T$,

$$\rho \int_0^T \Delta b(s; v) ds = \int_{I_\rho} \Delta b(s; v) ds + \eta^*, \quad \mathbb{E} |\eta^*|^2 = o(\rho^4), \quad (53)$$

$$\rho \int_0^T \mathbb{E} [\Delta H(s; v)] ds = \int_{I_\rho} \mathbb{E} [\Delta H(s; v)] ds + o(\rho^2), \quad (54)$$

and

$$\begin{aligned}
& \rho \int_0^T \mathbb{E} \left\{ \triangle H_x(s; v) X_s^{v,1} + \tilde{\mathbb{E}} \left[\triangle H_\mu(s; v) \tilde{X}_s^{v,1} \right] + \triangle b^*(s; v) P_s X_s^{v,1} \right\} ds \\
&= \int_{I_\rho} \mathbb{E} \left\{ \triangle H_x(s; v) X_s^{v,1} + \tilde{\mathbb{E}} \left[\triangle H_\mu(s; v) \tilde{X}_s^{v,1} \right] + \triangle b^*(s; v) P_s X_s^{v,1} \right\} ds \\
& \quad + o(\rho^2). \tag{55}
\end{aligned}$$

Lemma 5.2. *For the I_ρ above, $t \in [0, T]$, we also have*

$$\rho \int_0^t \triangle b(s; v) ds = \int_{I_\rho \cap [0, t]} \triangle b(s; v) ds + \eta_t^*, \quad \sup_{0 \leq t \leq T} \mathbb{E} |\eta_t^*|^2 = o(\rho^4). \tag{56}$$

The proof of the above lemma is essentially the same as Lemma 4.1 [18]. For the convenience of readers, we present the proof here.

Proof. Let $\phi_i(\cdot) \in L^2(\Omega; L^2(0, T; \mathbb{R}^{l_i}))$, $l_i \geq 1$, $i = 1, \dots, k$. Suppose

$$\sup_{0 \leq t \leq T} \mathbb{E} |\phi_1(t)|^2 < \infty$$

. Given $0 < \rho < 1$ and set $\delta = \rho^5$, then there exists a $n > 0$, we can find a process $\phi_i^\rho(\cdot)$ in the form of

$$\phi_i^\rho(t) = \sum_{j=0}^n \xi_i^j I_{[t_j, t_{j+1})}(t), \quad 1 \leq i \leq k,$$

with $0 = t_0 < t_1 < \dots < t_{n+1} = T$, $\max |t_{i+1} - t_i| < \delta$, ξ_i^j being $\mathcal{F}_{t_j}$ -measurable, s.t.

$$\sup_{0 \leq t \leq T} \mathbb{E} |\phi_1(t) - \phi_1^\rho(t)|^2 < \delta. \tag{57}$$

$$\sum_{i=2}^k \mathbb{E} \left(\int_0^T |\phi_i(t) - \phi_i^\rho(t)|^2 dt \right) < \delta. \tag{58}$$

Note that we can always choose the partition $\{t_j\}_{0 \leq j \leq n+1}$ independent of $i = 1, \dots, k$. Now letting

$$G = \bigcup_{j=0}^n [t_j, t_j + \rho(t_{j+1} - t_j)).$$

It's easy to see $|G| = \rho T$. Thus (53), (54), and (55) are proved by taking ϕ_i suitably. For any $s \in [0, T]$, we can always find a $m \geq 0$, s.t. $s \in [t_m, t_{m+1})$. Then we have

$$\begin{aligned}
& \sup_{0 \leq s \leq T} \mathbb{E} \left| \int_0^T I_{\{t \leq s\}} \left(1 - \frac{I_G(t)}{\rho} \right) \phi_1^\rho(t) dt \right|^2 \\
& \leq \sup_{0 \leq s \leq T} \mathbb{E} \left| \sum_{j=0}^{m-1} \xi_1^j \left[(t_{j+1} - t_j) - \frac{\rho(t_{j+1} - t_j)}{\rho} \right] + \xi_1^m \left[(s - t_m) - \frac{(s - t_m)}{\rho} \right] \right|^2 \\
& \quad + \sup_{0 \leq s \leq T} \mathbb{E} \left| \sum_{j=0}^{m-1} \xi_1^j \left[(t_{j+1} - t_j) - \frac{\rho(t_{j+1} - t_j)}{\rho} \right] \right|^2 \\
& \quad + \xi_1^m \left[(s - t_m) - \frac{\rho(t_{m+1} - t_m)}{\rho} \right]^2
\end{aligned}$$

$$\leq K\delta^2\rho^{-2} + K\delta^2, \quad (59)$$

where $I_G(t)$ is the indicator function of G . Thus, for each $1 \leq i \leq k$,

$$\begin{aligned} & \sup_{0 \leq s \leq T} \mathbb{E} \left| \int_0^T I_{\{t \leq s\}} \left(1 - \frac{I_G(t)}{\rho} \right) \phi_1(t) dt \right|^2 \\ & \leq \sup_{0 \leq s \leq T} \mathbb{E} \left| \int_0^T I_{\{t \leq s\}} \left(1 - \frac{I_G(t)}{\rho} \right) \phi_1(t) - I_{\{t \leq s\}} \left(1 - \frac{I_G(t)}{\rho} \right) \phi_1^\rho(t) dt \right|^2 \\ & \quad + K\delta^2\rho^{-2} \\ & \leq \mathbb{E} \left| \int_0^T \left(1 - \frac{I_G(t)}{\rho} \right) [\phi_1(t) - \phi_1^\rho(t)] dt \right|^2 + K\delta^2\rho^{-2} \\ & \leq \rho^{-2}T\delta + K\delta^2\rho^{-2}. \end{aligned} \quad (60)$$

Set $\phi_1(t) = \triangle b(t, v)$, then letting $\rho \rightarrow 0$, we finish the proof. $\square$

Lemma 5.3. *For any $\rho \in [0, 1]$, there exists a subset I_ρ of $[0, T]$, such that*

$$\lim_{\rho \rightarrow 0^+} \sup_{0 \leq t \leq T} \mathbb{E} \left[\left| \frac{X_t^{\hat{v},1} - \rho X_t^{v,1}}{\rho} \right|^2 \right] = 0. \quad (61)$$

where $\hat{v}$ is defined by (30) with I_ρ given here.

Proof. By (18) and lemma 5.2, we have

$$\begin{aligned} & X_t^{\hat{v},1} - \rho X_t^{v,1} \\ & = \int_0^t b_x(s) \left(X_s^{\hat{v},1} - \rho X_s^{v,1} \right) ds + \int_0^t \tilde{\mathbb{E}} \left[b_\mu(s) \left(\tilde{X}_s^{\hat{v},1} - \rho \tilde{X}_s^{v,1} \right) \right] ds \\ & \quad + \int_0^t (\triangle b(s; \hat{v}) - \rho \triangle b(s; v)) ds \\ & \quad + \int_0^t \sigma_x(s) \left(X_s^{\hat{v},1} - \rho X_s^{v,1} \right) ds + \int_0^t \tilde{\mathbb{E}} \left[\sigma_\mu(s) \left(\tilde{X}_s^{\hat{v},1} - \rho \tilde{X}_s^{v,1} \right) \right] dB_s. \end{aligned} \quad (62)$$

Thus, we can get

$$\begin{aligned} & \mathbb{E} \left| X_t^{\hat{v},1} - \rho X_t^{v,1} \right|^2 \\ & \leq K \int_0^t \mathbb{E} \left| X_s^{\hat{v},1} - \rho X_s^{v,1} \right|^2 ds + \sup_{0 \leq t \leq T} \mathbb{E} \left[\int_0^t (\triangle b(s; \hat{v}) - \rho \triangle b(s; v)) ds \right]^2. \end{aligned} \quad (63)$$

Notice that

$$\begin{aligned} & K \sup_{0 \leq t \leq T} \mathbb{E} \frac{1}{\rho^2} \left[\int_0^t (\triangle b(s; \hat{v}) - \rho \triangle b(s; v)) ds \right]^2 \\ & = K \sup_{0 \leq t \leq T} \frac{1}{\rho^2} \mathbb{E} |\eta_t^*|^2 = o(1). \end{aligned} \quad (64)$$

By Gronwall's inequality, we get (61). $\square$

Further more, inspired by [24], we also have the following lemma holds.

Lemma 5.4. *For any $\rho \in [0, 1]$, there exists a set $I_\rho \in [0, T]$ and a matrix value process $\Phi(t)$, s.t. $X_t^{\hat{v},1}$ is represented by the following*

$$X_t^{\hat{v},1} = \Phi(t) \int_0^t \Phi^{-1}(s) \triangle b(s; \hat{v}) ds + A_t^*, \quad (65)$$

where

$$\lim_{\rho \rightarrow 0+} \sup_{0 \leq t \leq T} \mathbb{E} \left[\left| \frac{A_t^*}{\rho} \right|^2 \right] = 0. \quad (66)$$

Proof. Let $\Phi(t)$ be the unique solution of the following matrix value SDE:

$$\Phi(t) = I + \int_0^t \left\{ b_x(s) + \tilde{\mathbb{E}}[b_\mu(s)] \right\} \Phi(s) ds + \int_0^t \left\{ \sigma_x(s) + \tilde{\mathbb{E}}[\sigma_\mu(s)] \right\} \Phi(s) dB_s, \quad (67)$$

and set

$$\begin{aligned} \Psi(t) &= I + \int_0^t \Psi(s) \left\{ - \left(b_x(s) + \tilde{\mathbb{E}}[b_\mu(s)] \right) + \left(\sigma_x(s) + \tilde{\mathbb{E}}[\sigma_\mu(s)] \right)^2 \right\} ds \\ &\quad - \int_0^t \Psi(s) \left\{ \sigma_x(s) + \tilde{\mathbb{E}}[\sigma_\mu(s)] \right\} dB_s. \end{aligned} \quad (68)$$

Applying Itô's formula to $[\Psi_t \Phi_t]$, we can easily get $d[\Psi_t \Phi_t] = 0$, which means $\Psi_t \Phi_t \equiv I$, i.e. $\Psi_t = \Phi_t^{-1}$. Applying Itô's formula to $d[\Psi_t X_t^{\hat{v},1}]$, by Lemma 5.3, we then get our desire result. $\square$

Now we continue to derive the expansion. Applying Itô's formula to $Y_t := X_t^{\hat{v},1} X_t^{*\hat{v},1}$, we have

$$\begin{aligned} dY_t &= \left\{ Y_t b_x^*(t) + X_t^{\hat{v},1} \tilde{\mathbb{E}} \left[\tilde{X}_t^{*\hat{v},1} b_\mu^*(t) \right] + X_t^{\hat{v},1} \triangle b^*(t; \hat{v}) \right. \\ &\quad \left. + b_x(t) Y_t + \tilde{\mathbb{E}} \left[b_\mu(t) \tilde{X}_t^{\hat{v},1} \right] X_t^{*\hat{v},1} + \triangle b(t; \hat{v}) X_t^{*\hat{v},1} \right. \\ &\quad \left. + \left(\sigma_x(t) X_t^{\hat{v},1} + \tilde{\mathbb{E}} \left[\sigma_\mu(t) X_t^{\hat{v},1} \right] \right) \left(X_t^{*\hat{v},1} \sigma_x^*(t) + \tilde{\mathbb{E}} \left[X_t^{*\hat{v},1} \sigma_\mu^*(t) \right] \right) \right\} dt \\ &\quad + \left\{ Y_t \sigma_x^*(t) + X_t^{\hat{v},1} \tilde{\mathbb{E}} \left[\tilde{X}_t^{*\hat{v},1} \sigma_\mu^*(t) \right] + \sigma_x(t) Y_t + \tilde{\mathbb{E}} \left[\sigma_\mu(t) \tilde{X}_t^{\hat{v},1} \right] X_t^{*\hat{v},1} \right\} dB_t. \end{aligned} \quad (69)$$

Applying Itô's formula to $P_t Y_t$, according to (61), we obtain

$$\begin{aligned} &\mathbb{E} \int_0^T \text{Trace} \{ H_{xx}(s) X_s^{\hat{v},1} X_s^{*\hat{v},1} \} ds + 2\mathbb{E} \tilde{\mathbb{E}} \int_0^T \text{Trace} \{ H_{x\mu}(s) X_s^{\hat{v},1} \tilde{X}_s^{*\hat{v},1} \} ds \\ &\quad + \mathbb{E} \tilde{\mathbb{E}} \int_0^T \text{Trace} \{ H_{y\mu}(s) \tilde{X}_s^{\hat{v},1} \tilde{X}_s^{*\hat{v},1} \} ds \\ &\quad + \mathbb{E} \tilde{\mathbb{E}} \int_0^T \text{Trace} \{ H_{\mu\mu}(s) \tilde{X}_s^{\hat{v},1} \tilde{X}_s^{*\hat{v},1} \} ds \\ &= \mathbb{E} \int_0^T \text{Trace} \{ P_s X_s^{\hat{v},1} \triangle b^*(t; \hat{v}) + P_s \triangle b(s; \hat{v}) X_s^{*\hat{v},1} \} ds + o(\rho^2) \\ &= 2\mathbb{E} \int_0^T [\triangle b^*(s; \hat{v}) P_s X_s^{\hat{v},1}] ds + o(\rho^2). \end{aligned} \quad (70)$$

Putting (70) into (52), we conclude

$$\begin{aligned}
J(\hat{v}) - J(u) &= \mathbb{E} \int_0^T \Delta H(s; \hat{v}) ds + \mathbb{E} \int_0^T \Delta H_x(s; \hat{v}) X_s^{\hat{v},1} ds \\
&\quad + \mathbb{E} \tilde{\mathbb{E}} \int_0^T \Delta H_\mu(s; \hat{v}) \tilde{X}_s^{\hat{v},1} ds \\
&\quad + \mathbb{E} \int_0^T [\Delta b^*(s; \hat{v}) P_s X_s^{\hat{v},1}] ds + o(\rho^2).
\end{aligned} \tag{71}$$

From Lemma 5.1, (61) and (71), we obtain

$$\begin{aligned}
J(\hat{v}) - J(u) &= \mathbb{E} \int_0^T \Delta H(s; \hat{v}) ds + \rho \mathbb{E} \int_0^T \Delta H_x(s; \hat{v}) X_s^{v,1} ds \\
&\quad + \rho \mathbb{E} \tilde{\mathbb{E}} \int_0^T \Delta H_\mu(s; \hat{v}) \tilde{X}_s^{v,1} ds + \rho \mathbb{E} \int_0^T [\Delta b^*(s; \hat{v}) P_s X_s^{v,1}] ds \\
&\quad + o(\rho^2) \\
&= \mathbb{E} \int_{I_\rho} \Delta H(s; v) ds + \rho \mathbb{E} \int_{I_\rho} \Delta H_x(s; v) X_s^{v,1} ds \\
&\quad + \rho \mathbb{E} \tilde{\mathbb{E}} \int_{I_\rho} \Delta H_\mu(s; v) \tilde{X}_s^{v,1} ds + \rho \mathbb{E} \int_{I_\rho} [\Delta b^*(s; v) P_s X_s^{v,1}] ds \\
&\quad + o(\rho^2).
\end{aligned} \tag{72}$$

Finally, according to (55), we have

$$\begin{aligned}
&J(\hat{v}) - J(u) \\
&= \rho \mathbb{E} \int_0^T \Delta H(s; v) ds + \rho^2 \mathbb{E} \int_0^T \Delta H_x(s; v) X_s^{v,1} ds \\
&\quad + \rho^2 \mathbb{E} \tilde{\mathbb{E}} \int_0^T \Delta H_\mu(s; v) \tilde{X}_s^{v,1} ds + \rho^2 \mathbb{E} \int_0^T [\Delta b^*(s; v) P_s X_s^{v,1}] ds \\
&\quad + o(\rho^2).
\end{aligned} \tag{73}$$

6. The proofs of the stochastic maximum principle. Although the first-order SMP has been obtained by [5], we give a proof here for completeness. In fact, after the preparation of the previous sections which will also be needed in the proof of the second-order SMP, this proof does not take too much extra effort.

Proof of first-order SMP: Since (X^u, u) is an optimal pair of our system, it follows from (73) that

$$J(\hat{v}) - J(u) = \rho \mathbb{E} \int_0^T \Delta H(s; v) ds + o(\rho) \geq 0. \tag{74}$$

for any $\rho \in [0, T]$, $\forall v(\cdot) \in \mathcal{U}$. Setting $\rho \rightarrow 0+$, we obtain

$$\mathbb{E} \int_0^T \Delta H(s; v) ds \geq 0, \quad \forall v(\cdot) \in \mathcal{U}. \tag{75}$$

Then we can deduce that, for any fixed $v \in \mathcal{U}$, there exists a null subset $S^v \subset [0, T] \times \Omega$, such that for each $(t, \omega) \in (S^v)^c$,

$$\Delta H(s; v) \geq 0. \tag{76}$$

Otherwise, suppose that

$$A = \{(s, \omega) : \Delta H(s; v^*) < 0\}$$

has positive measure in $[0, T] \times \Omega$, for a $v^* \in \mathcal{U}$. Let

$$\hat{v}^* = v^* 1_A + u 1_{A^c}.$$

Then,

$$\mathbb{E} \int_0^T \Delta H(s; \hat{v}^*) ds = \mathbb{E} \int_0^T \Delta H(s; v^*) 1_A ds < 0. \quad (77)$$

This contradicts from (75).

Select a countable dense subset $\{v_s^{(i)}\}_{i=1}^\infty \subset U$, set

$$S_0 = \bigcup_{i=1}^\infty S^{v^{(i)}}.$$

Then, S_0 is a null subset of $[0, r] \times \Omega$, and for $(t, \omega) \in S := (S_0)^c$, we get

$$\Delta H(s; v^{(i)}) \geq 0. \quad (78)$$

By Fubini's theorem, it is easy to see that there exists a null subset T_0 of $[0, T]$, such that $\forall t \in T_0^c$, (78) holds *a.s.*

Finally, from the continuity of the function and the denseness of $\{v^{(i)}\}_{i=1}^\infty$, we have for $t \in (T_0)^c$,

$$\Delta H(s; v) \geq 0, \quad \forall v \in U, \text{ a.s.} \quad (79)$$

□

Now, we proceed to presenting the proof of the second-order stochastic maximum principle for singular generalized mean-field control problem.

Proof of Theorem 3.2. The optimality and the singularity imply that

$$\Delta H(t; v) \equiv 0, \quad \forall v \in V.$$

According to (73), we have

$$\begin{aligned} & \mathbb{E} \int_{t_1}^{t_2} \left\{ \Delta H_x(s; v) X_s^{v,1} + \tilde{\mathbb{E}} \left[\Delta H_\mu(s; v) \tilde{X}_s^{v,1} \right] + \Delta b^*(s; v) P_s X_s^{v,1} \right\} ds \\ & \geq 0, \quad \forall v \in \mathcal{V}(t_1, t_2), \text{ a.s.}, \end{aligned} \quad (80)$$

where

$$\begin{aligned} \mathcal{V}(t_1, t_2) := & \left\{ v(\cdot) \in \mathcal{U} \mid v_t \in V, \text{ a.s., a.e., } t \in [t_1, t_2]; v(t) = u(t), \right. \\ & \left. t \in [0, T] \setminus [t_1, t_2] \right\}. \end{aligned}$$

As in [11][23], denote by $\{t_i\}_{i=1}^\infty$ the collection of all rational numbers in $[0, T]$, and $\{v_k\}_{k=1}^\infty$ a dense subset of V . Because of the fact that $\mathcal{F}_t$ is countability generated for $t \in [0, T]$, we can assume $\{A_{i,j}\}_{j=1}^\infty$ generates $\mathcal{F}_{t_i}$, $i = 1, 2, \dots$. For any $\tau \in [t_i, T)$ and $\theta \in (0, T - \tau)$, write $E_\theta^i = [\tau, \tau + \theta)$, and define

$$v_{i,j}^k(t, \omega) = \begin{cases} v_k(t, \omega), & (t, \omega) \in E_\theta^i \times A_{i,j}, \\ u(t, \omega), & (t, \omega) \in (E_\theta^i \times A_{i,j})^c. \end{cases} \quad (81)$$

Let X_{ij}^{1k} be the solution to the equation (18) with respect to $v_{i,j}^k(\cdot)$. Notice that we can always choose suitable I_θ , such that $I_\theta \cap E_\theta^i = E_\theta^i$. So Lemma 5.4 holds for X_{ij}^{1k} .

By Lemma 4.1 [25], lemma 4.2 and Lebesgue differential theorem, there is a null subset $T_{ij}^k \subset [0, T]$ such that for $\tau \in (T_{ij}^k)^c$, we have

$$\begin{aligned}
0 &\leq \lim_{\theta \rightarrow 0+} \frac{1}{\theta^2} \int_{\tau}^{\tau+\theta} \mathbb{E} \left\{ \Delta H_x(s; v_{i,j}^k) X_{ij}^{1k}(s) + \tilde{\mathbb{E}} \left[\Delta H_{\mu}(s; v_{i,j}^k) \tilde{X}_{ij}^{1k}(s) \right] \right. \\
&\quad \left. + \Delta b^*(s; v_{i,j}^k) P_s X_{ij}^{1k}(s) \right\} ds \\
&= \lim_{\theta \rightarrow 0+} \frac{1}{\theta^2} \int_{\tau}^{\tau+\theta} \mathbb{E} \left\{ \Delta H_x(s; v_{i,j}^k) \Phi(s) \int_{\tau}^s \Phi^{-1}(r) \Delta b(r; v_k) 1_{A_{ij}} dr \right. \\
&\quad \left. + \tilde{\mathbb{E}} \left[\Delta H_{\mu}(s; v_{i,j}^k) \Phi(s) \int_{\tau}^s \Phi^{-1}(r) \Delta \tilde{b}(r; v_k) 1_{A_{ij}} dr \right] \right. \\
&\quad \left. + \Delta b^*(r; v_{i,j}^k) P_s \Phi(s) \int_{\tau}^s \Phi^{-1}(r) \Delta b(r; v_k) 1_{A_{ij}} dr \right\} ds \\
&= \mathbb{E} \left\{ \Delta H_x(\tau; v_k) \Delta b(\tau; v_k) 1_{A_{ij}} + \tilde{\mathbb{E}} \left[\Delta H_{\mu}(\tau; v_k) \Delta \tilde{b}(\tau; v_k) 1_{A_{ij}} \right] \right. \\
&\quad \left. + \Delta b^*(\tau; v_k) P_{\tau} \Delta b(\tau; v_k) 1_{A_{ij}} \right\}. \tag{82}
\end{aligned}$$

Set

$$T_0 = \bigcup_{1 \leq i, j, k \leq \infty} T_{i,j}^k.$$

Then, T_0 is a null subset of $[0, T]$. For $s \in [0, T] \setminus T_0$ and i , we deduce that

$$\begin{aligned}
&\mathbb{E} \left\{ \Delta H_x(s; v_k) \Delta b(s; v_k) 1_{A_{ij}} + \tilde{\mathbb{E}} \left[\Delta H_{\mu}(s; v_k) \Delta \tilde{b}(s; v_k) 1_{A_{ij}} \right] \right. \\
&\quad \left. + \Delta b^*(s; v_k) P_s \Delta b(s; v_k) 1_{A_{ij}} \right\} \geq 0, \quad \forall j, k = 1, 2, \dots, \tag{83}
\end{aligned}$$

which means

$$\begin{aligned}
&\mathbb{E} \left\{ \Delta H_x(s; v) \Delta b(s; v) 1_A + \tilde{\mathbb{E}} \left[\Delta H_{\mu}(s; v) \Delta \tilde{b}(s; v) 1_A \right] \right. \\
&\quad \left. + \Delta b^*(s; v) P(s) \Delta b(s; v) 1_A \right\} \geq 0, \quad \forall v \in V, \quad A \in \mathcal{F}_t. \tag{84}
\end{aligned}$$

By virtue of the continuity of the function and the denseness of $\{v_k\}_{k=1}^{\infty}$, we finish the proof. $\square$

Remark 2. We now come back to Example 1.1. It is not hard to check that the second order adjoint process $(P_t, Q_t) \equiv (1, 0)$. Then

$$\begin{aligned}
&\Delta H_x(t; v) \Delta b(t; v) + \tilde{\mathbb{E}} \left[\Delta H_{\mu}(t; v) \Delta \tilde{b}(t; v) \right] \\
&\quad + \Delta b^*(t; v) P_t \Delta b(t; v) = v_t^2 \geq 0, \quad \forall v \in U, a.s..
\end{aligned}$$

So we can say $u_t \equiv 0$ is the only candidate for optimal controls.

REFERENCES

- [1] V. Arkin and I. Saksonov, Necessary optimality conditions of optimality in the problems of control of stochastic differential-equations, *Doklady Akademii Nauk SSSR.*, **244** (1979), 11–15.
- [2] D. J. Bell and D. H. Jacobson, *Singular Optimal Control Problems*, Vol. 117. Elsevier, 1975.

- [3] A. Bensoussan, Lectures on stochastic control. *Nonlinear filtering and stochastic control*, (1982), 1–62.
- [4] J. M. Bismut, An introductory approach to duality in optimal stochastic control, *SIAM Review*, **20.1** (1978), 62–78.
- [5] R. Buckdahn, J. Li and J. Ma, A Stochastic Maximum Principle for General Mean-Field Systems. *Applied Mathematics and Optimization*, **74.3** (2016), 507–534.
- [6] R. Buckdahn, J. Li and S. Peng, Mean-field backward stochastic differential equations and related partial differential equations, *Stoch. Proc. App.*, **119.10** (2009), 3133–3154.
- [7] R. Buckdahn, J. Li, S. Peng and C. Rainer, Mean-field stochastic differential equations and associated PDEs, preprint [arXiv:1407.1215](#).
- [8] P. Cardaliaguet, Weak solutions for first order mean field games with local coupling, *Analysis and Geometry in Control Theory and its Applications*, (2015), 111–158.
- [9] R. Gabasov, F. M. Kirillova, High order necessary conditions for optimality, *SIAM J. Control*, **10** (1972), 127–168.
- [10] U. G. Haussmann, *A Stochastic Maximum Principle for Optimal Control of Diffusions*, Essex, UK: Longman Scientific and Technical, 1986.
- [11] U. G. Haussmann, General necessary conditions for optimal control of stochastic systems, *Math. Program. Study*, **6** (1976), 30–48.
- [12] M. A. Kazemi-Dehkordi, Necessary conditions for optimality of singular controls, *J. Optim. Theor. Appl.*, **43** (1984), 629–637.
- [13] A. J. Krener, The high-order maximum principle and its application to singular extremals, *SIAM J. Control*, **15** (1977), 256–293.
- [14] H. J. Kushner, On the stochastic maximum principle: fixed time of control, *Journal of Mathematical Analysis and Applications*, **11** (1965), 78–92.
- [15] H. J. Kushner, Necessary conditions for continuous parameter stochastic optimization problems, *SIAM Journal of Control*, **10** (1972), 550–565.
- [16] J. Li, Stochastic maximum principle in the mean-field controls, *Automatica*, **48** (2012), 366–373.
- [17] Q. Lu, Second order necessary conditions for optimal control problems of stochastic evolution equations, *Control Conference (CCC), 2016 35th Chinese. IEEE*, (2016), 2620–2625.
- [18] L. Mou and J. Yong, A variational formula for stochastic controls and some applications, *Pure Appl. Math. Q.*, **3.2** (2007), 539–567.
- [19] K. Mizukami and H. Wu, New necessary conditions for optimality of singular controls in optimal control problems, *Int. J. Systems Sci.*, **23** (1992), 1335–1345.
- [20] E. Pardoux and S. Peng, Adapted solution of a backward stochastic differential equation, *System Control Lett.*, **14.1** (1990), 55–61.
- [21] S. Peng, A general stochastic maximum principle for optimal control problem, *SIAM J. Control and Optimization*, **28.4** (1990), 966–979.
- [22] L. S. Pontryagin, V. G. Boltyanskii, R. V. Gamkerlidze and E. F. Mischenko. *The Mathematical Theory of Optimal Control Processes*, John Wiley, New York, 1962.
- [23] S. J. Tang, A second-order maximum principle for singular optimal stochastic controls, *Discrete and continuous dynamical system series B*, **14.4** (2010), 1581–1599.
- [24] J. Yong and X.Y. Zhou, *Stochastic Controls: Hamiltonian Systems and HJB Equations*, Springer-Verlag, New York, Berlin, 2000.
- [25] H. Zhang and X. Zhang, Pointwise second-order necessary conditions for stochastic optimal controls, Part I: The case of convex control constraint. *SIAM Journal on Control and Optimization*, **53.4** (2015), 2267–2296.

Received xxxx 20xx; revised xxxx 20xx.

E-mail address: guohancheng1989@gmail.com

E-mail address: jiexiong@umac.mo